

A. Details of the Client/Person Ordering the Report Client: <input type="text" value="Wessex RFCA"/> Address: <input type="text" value="Mount House"/> <input type="text" value="Mount Street"/> <input type="text" value="Taunton"/> <input type="text" value="Devon"/> <input type="text" value="TA1 3QE"/>	B. Reason for Producing this Report Purpose of this report: <div style="border: 1px solid black; padding: 5px; min-height: 40px;">5 year test and inspection to assess the condition of the electrical installation.</div> Date(s) on which Inspection: <input type="text" value="30/11/2020"/> and testing was carried out																				
C. Details of the Installation which is the Subject of this Report Installation: <input type="text" value="Yeovil Army Reserve"/> Occupier: <input type="text" value="Yeovil Army Reserve"/> Address: <input type="text" value="675 Squadron AAC"/> <input type="text" value="Army Reserve centre"/> <input type="text" value="Southville"/> <input type="text" value="Yeovil"/> <input type="text" value="BA21 4JA"/> Record of Installation available: <input type="text" value="N/A"/> Records held By: <input type="text" value="N/A"/>	<table style="width:100%;"> <tr> <td style="width:33%;">Description of premises:</td> <td style="width:16.5%; text-align: center;">Domestic <input type="text" value="N/A"/></td> <td style="width:16.5%; text-align: center;">Commercial <input checked="" type="checkbox"/></td> <td style="width:34.5%; text-align: center;">Industrial <input type="text" value="N/A"/></td> </tr> <tr> <td>Other:</td> <td colspan="3"><input type="text" value="N/A"/></td> </tr> <tr> <td>Estimated age of wiring system:</td> <td colspan="3" style="text-align: right;"><input type="text" value="5"/> yrs</td> </tr> <tr> <td>Evidence of alterations or additions:</td> <td style="text-align: center;"><input type="text" value="N/A"/></td> <td style="text-align: center;">If yes estimated Age</td> <td style="text-align: right;"><input type="text" value="N/A"/> yrs</td> </tr> <tr> <td colspan="2">Date of previous inspection:</td> <td colspan="2" style="text-align: right;"><input type="text" value="Not Known"/></td> </tr> </table>	Description of premises:	Domestic <input type="text" value="N/A"/>	Commercial <input checked="" type="checkbox"/>	Industrial <input type="text" value="N/A"/>	Other:	<input type="text" value="N/A"/>			Estimated age of wiring system:	<input type="text" value="5"/> yrs			Evidence of alterations or additions:	<input type="text" value="N/A"/>	If yes estimated Age	<input type="text" value="N/A"/> yrs	Date of previous inspection:		<input type="text" value="Not Known"/>	
Description of premises:	Domestic <input type="text" value="N/A"/>	Commercial <input checked="" type="checkbox"/>	Industrial <input type="text" value="N/A"/>																		
Other:	<input type="text" value="N/A"/>																				
Estimated age of wiring system:	<input type="text" value="5"/> yrs																				
Evidence of alterations or additions:	<input type="text" value="N/A"/>	If yes estimated Age	<input type="text" value="N/A"/> yrs																		
Date of previous inspection:		<input type="text" value="Not Known"/>																			
D. Extent and Limitations Inspection and Testing Extent of Electrical Installation covered by this report: <div style="border: 1px solid black; padding: 5px; min-height: 20px;">Fixed wiring only.</div> Agreed limitations including the reasons (See regulation 653.2) <div style="border: 1px solid black; padding: 5px; min-height: 20px;">In accordance with guidance note 3 and BS7671.</div> <div style="display: flex; justify-content: space-between; margin-top: 10px;"> <div> Operational Limitations including the reasons (See page No <input type="text" value="N/A"/>) <div style="border: 1px solid black; padding: 5px; min-height: 20px;">None</div> </div> <div style="width: 40%;"> Agreed with name <input type="text" value="Site"/> </div> </div> <p style="font-size: small;">This inspection and testing detailed in this report and accompanying schedules have been carried out in accordance with BS7671:2018 (IET Wiring Regulations) as amended to <input type="text" value="July 2018"/> It should be noted that cables concealed within trunking and conduits, under floors, in roof spaces, and generally within the fabric of the building or underground, have NOT been inspected unless specifically agreed between the client and inspector prior to the inspection. An inspection should be made within an accessible roof space housing other electrical equipment.</p>																					
E. Summary of the Condition of the Installation General condition of the installations (In terms of electrical safety) <div style="border: 1px solid black; padding: 5px; min-height: 20px;">Installation will become satisfactory once C2 observations are corrected.</div> <div style="display: flex; justify-content: space-between; margin-top: 10px;"> <div>Overall assessment of the installation</div> <div style="border: 1px solid black; padding: 2px 5px;">Unsatisfactory</div> <div style="font-size: x-small;">*An unsatisfactory assessment indicates that dangerous (code C1) and/or potentially dangerous (code C2) conditions have been identified.</div> </div>																					
F. Recommendations <p style="font-size: x-small;">Where the overall assessment of the suitability of the installation for continued use above is stated as UNSATISFACTORY, I recommend that any observations classified as 'Danger present' (code C1) or 'Potentially dangerous' (code C2) are acted upon as a matter of urgency. Investigation without delay is recommended for observations identified as 'further investigation required' (code FI). Observation classified as 'Improvement recommended' (code C3) should be given due consideration. Subject to the necessary remedial action being taken I recommend that the installation is further inspected and tested by <input type="text" value="30/11/2025"/></p>																					
G. Declaration I, being the person(s) responsible for the inspection and testing of the electrical installation (as indicated by My signatures below), particulars of which are described above, having exercised reasonable skill and care when carrying out the inspection and testing, hereby declare that the information in this report, including the observations and attached schedules, provides an accurate assessment of the condition of the electrical installation taking into account the stated extent and limitations in section D of this report. <table style="width:100%; margin-top: 10px;"> <tr> <td style="width:60%;"> Trading Title and address <input type="text" value="I J Cannings & Son Ltd.,"/> <input type="text" value="Stratford House Water Bridge Court,"/> <input type="text" value="Matford Park Road,"/> <input type="text" value="Exeter,"/> <input type="text" value="Devon, EX2 8EX"/> </td> <td style="width:40%;"> NICEIC Enrolment Number <input type="text" value="9140"/> Branch No. (If Applicable) <input type="text" value="n/a"/> </td> </tr> </table> <div style="margin-top: 10px;"> Inspected and tested by: <table style="width:100%;"> <tr> <td style="width:25%;">Name <input type="text" value="Jamie Paulton"/></td> <td style="width:25%;">Position <input type="text" value="Approved Electrician"/></td> <td style="width:25%;">Signature </td> <td style="width:25%;">Date <input type="text" value="11/12/2020"/></td> </tr> <tr> <td colspan="4">Report authorised for issue by:</td> </tr> <tr> <td>Name <input type="text" value="Callum Harrison"/></td> <td>Position <input type="text" value="Approved Electrician"/></td> <td>Signature </td> <td>Date <input type="text" value="11/12/2020"/></td> </tr> </table> </div>		Trading Title and address <input type="text" value="I J Cannings & Son Ltd.,"/> <input type="text" value="Stratford House Water Bridge Court,"/> <input type="text" value="Matford Park Road,"/> <input type="text" value="Exeter,"/> <input type="text" value="Devon, EX2 8EX"/>	NICEIC Enrolment Number <input type="text" value="9140"/> Branch No. (If Applicable) <input type="text" value="n/a"/>	Name <input type="text" value="Jamie Paulton"/>	Position <input type="text" value="Approved Electrician"/>	Signature	Date <input type="text" value="11/12/2020"/>	Report authorised for issue by:				Name <input type="text" value="Callum Harrison"/>	Position <input type="text" value="Approved Electrician"/>	Signature	Date <input type="text" value="11/12/2020"/>						
Trading Title and address <input type="text" value="I J Cannings & Son Ltd.,"/> <input type="text" value="Stratford House Water Bridge Court,"/> <input type="text" value="Matford Park Road,"/> <input type="text" value="Exeter,"/> <input type="text" value="Devon, EX2 8EX"/>	NICEIC Enrolment Number <input type="text" value="9140"/> Branch No. (If Applicable) <input type="text" value="n/a"/>																				
Name <input type="text" value="Jamie Paulton"/>	Position <input type="text" value="Approved Electrician"/>	Signature	Date <input type="text" value="11/12/2020"/>																		
Report authorised for issue by:																					
Name <input type="text" value="Callum Harrison"/>	Position <input type="text" value="Approved Electrician"/>	Signature	Date <input type="text" value="11/12/2020"/>																		
H. Schedule(s) The attached schedule(s) are part of this document and this report is valid only when they are attached to it. <div style="display: flex; justify-content: space-between; margin-top: 5px;"> <div><input type="text" value="2"/> Schedule(s) of inspection and</div> <div><input type="text" value="2"/> Schedule(s) of test results are attached</div> </div>																					

I. Supply Characteristics and Earthing Arrangements				Nature of Supply Parameters		Supply protective device	
Earthing Arrangements		Number and Type of Live Conductors					
TN-S	<input checked="" type="checkbox"/>	a.c.	<input checked="" type="checkbox"/>	d.c.	N/A	Nominal Voltage $U^{(1)}$	400 V
TN-C-S	N/A	1-Phase (2 wire)	N/A	1-Phase (3 wire)	<input checked="" type="checkbox"/>	Nominal Voltage $U_0^{(1)}$	230 V
TN-C	N/A	2-Phase (3 wire)	N/A	3 Wire	N/A	Nominal frequency $f^{(1)}$	50 Hz
TT	N/A	3-Phase (3 wire)	N/A	3-Phase (4 wire)	N/A	Prospective fault current $I_{pf}^{(2)}$	1.57 kA
IT	N/A	Other	N/A		N/A	External loop impedance $Z_e^{(2)}$	0.15 Ω
		Confirmation of supply polarity		<input checked="" type="checkbox"/>		Number of supplies	1
				(Note: (1) by enquiry, (2) by enquiry or by measurement)			
						Type	LIM
						Nominal current rating	LIM A
						Short circuit capacity	N/A kA

J. Particulars of Installation Referred to in the Report			
Means of earthing		Details of installation Earth Electrode (where applicable)	
Distributor's facility	<input checked="" type="checkbox"/>	Type (e.g. rod(s), tape etc.)	N/A
Installation earth electrode	N/A	Resistance to Earth	N/A Ω
		Location	N/A
		Method of measurement	N/A

Main Protective Conductors				Tick boxes and enter details as applicable	
Earthing Conductor	Material	Copper	csa	16	mm ²
				Continuity Verified	<input checked="" type="checkbox"/>
				Connection Verified	<input checked="" type="checkbox"/>
Main protective bonding conductors	Material	Copper	csa	16	mm ²
				Continuity Verified	<input checked="" type="checkbox"/>
				Connection Verified	<input checked="" type="checkbox"/>
Bonding of Incoming Service				Maximum Demand (Load)	
Water installation pipes	<input checked="" type="checkbox"/>	Gas installation pipes	<input checked="" type="checkbox"/>	Structural Steel	N/A
Oil installation pipes	N/A	Lightning protection	<input checked="" type="checkbox"/>		
Please State				100 Amps	
Other incoming service(s)				Protective measure(s) against electric shock	
N/A				ADS	

Main Switch / Switch-Fuse / Circuit-Breaker / RCD			
Location	Ground floor lecture room 1		
Type BS(EN)	60947-3	No of poles	3
Supply Conductors material	Copper	Supply Conductors csa	25 mm ²
		Current rating	N/A A
		Fuse/Device rating or setting	N/A A
		Voltage rating	N/A V
		if RCD main switch	
		Rated residual operation current, $I_{\Delta n}$	
		N/A mA	
		Rated time delay	
		N/A ms	
		RCD Operating time at, $I_{\Delta n}$	
		N/A ms	

K. Observations		
Referring to the attached schedule(s) of Inspection and Test Results, and subject to the limitations specified at the Extent and Limitations of the Inspection and testing section.		
No remedial action is required. N/A The following observations are made <input checked="" type="checkbox"/>		
Item No	Observations	Code
1	4.0 CONSUMER UNIT(S) / DISTRIBUTION BOARD(S) 4.21 Confirmation that ALL conductor connections, including connections to bus bars, are correctly located in terminals and are tight and secure (526.1)	C3
2	Further assessment is required for maximum demand(load) & diversity(Appendix 'A' pg 121 of on site guide) for this 240V single phase installation. Assuming the main cutout is fuse is 100A. Both distribution boards have many ring, lighting & water heater circuits plus DB R has 3x 50Amp shower circuits. With both distribution	FI
--Observations continue on continuation sheet(s)--		
One of the following codes, as appropriate, has been allocated to each of the observations made above to indicate to the person(s) responsible for the installation the degree of urgency for remedial action.		
C1 - Danger present. Risk of injury. Immediate remedial action required	0	
C2 - Potentially dangerous - urgent remedial action required	5	
C3 - Improvement recommended	3	
FI - Further investigation required without delay	1	

CONDITION REPORT INSPECTION SCHEDULE FOR DOMESTIC AND SIMILAR PREMISES WITH UP TO 100A SUPPLY

Note: this form is suitable for many types of smaller installations, not exclusively domestic.

Outcomes	Acceptable condition	✓	Unacceptable condition	State C1 or C2	Improvement recommended	State C3	Further investigation	FI	Not verified	N/V	Limitation	LIM	Not applicable	N/A
Item No	Description										Outcome		Comments	
1.0	EXTERNAL CONDITION OF INTAKE EQUIPMENT (VISUAL INSPECTION ONLY)													
1.1	Service cable										✓		No	
1.2	Service head										✓		No	
1.3	Earthing arrangement										✓		No	
1.4	Meter tails										✓		No	
1.5	Metering equipment										✓		No	
1.6	Isolator (where present)										N/A		No	
2.0	PRESENCE OF ADEQUATE ARRANGEMENTS FOR OTHER SOURCES SUCH AS MICROGENERATORS (551.6; 551.7)										N/A		No	
3.0	EARTHING / BONDING ARRANGEMENTS (411.3; Chap 54)													
3.1	Presence and condition of distributor's earthing arrangement (542.1.2.1; 542.1.2.2)										✓		No	
3.2	Presence and condition of earth electrode connection where applicable (542.1.2.3)										N/A		No	
3.3	Provision of earthing/bonding labels at all appropriate locations (514.13.1)										✓		No	
3.4	Confirmation of earthing conductor size (542.3; 543.1.1)										✓		No	
3.5	Accessibility and condition of earthing conductor at MET (543.3.2)										✓		No	
3.6	Confirmation of main protective bonding conductor sizes (544.1)										✓		No	
3.7	Condition and accessibility of main protective bonding conductor connections (543.3.2; 544.1.2)										✓		No	
3.8	Accessibility and condition of other protective bonding connections (543.3.1; 543.3.2)										✓		No	
4.0	CONSUMER UNIT(S) / DISTRIBUTION BOARD(S)													
4.1	Adequacy of working space/accessibility to consumer unit/distribution board (132.12; 513.1)										✓		No	
4.2	Security of fixing (134.1.1)										✓		No	
4.3	Condition of enclosure(s) in terms of IP rating etc (416.2)										✓		No	
4.4	Condition of enclosure(s) in terms of fire rating etc (421.1.201; 526.5)										✓		No	
4.5	Enclosure not damaged/deteriorated so as to impair safety (651.2)										✓		No	
4.6	Presence of main linked switch (as required by 462.1.201)										✓		No	
4.7	Operation of main switch (functional check) (643.10)										✓		No	
4.8	Manual operation of circuit-breakers and RCDs to prove disconnection (643.10)										✓		No	
4.9	Correct identification of circuit details and protective devices (514.8.1; 514.9.1)										✓		No	
4.10	Presence of RCD six-monthly test notice at or near consumer unit/distribution board (514.12.2)										✓		No	
4.11	Presence of non-standard (mixed) cable colour warning notice at or near consumer unit/distribution board (514.14)										✓		No	
4.12	Presence of alternative supply warning notice at or near consumer unit/distribution board (514.15)										N/A		No	
4.13	Presence of other required labelling (please specify) (Section 514)										✓		No	
4.14	Compatibility of protective devices, bases and other components; correct type and rating (No signs of unacceptable thermal damage, arcing or overheating) (411.3.2; 411.4; 411.5; 411.6; Sections 432, 433)										✓		No	
4.15	Single-pole switching or protective devices in line conductor only (132.14.1; 530.3.3)										✓		No	
4.16	Protection against mechanical damage where cables enter consumer unit/distribution board (132.14.1; 522.8.1; 522.8.5; 522.8.11)										✓		No	
4.17	Protection against electromagnetic effects where cables enter consumer unit/distribution board/enclosures (521.5.1)										✓		No	
4.18	RCD(s) provided for fault protection - includes RCBOs (411.4.204; 411.5.2; 531.2)										✓		No	
4.19	RCD(s) provided for additional protection/requirements - includes RCBOs (411.3.3; 415.1)										✓		No	
4.20	Confirmation of indication that SPD is functional (651.4)										N/A		No	
4.21	Confirmation that ALL conductor connections, including connections to busbars, are correctly located in terminals and are tight and secure (526.1)										C3 (see section K)		Yes	
4.22	Adequate arrangements where a generating set operates as a switched alternative to the public supply (551.6)										N/A		No	
4.23	Adequate arrangements where a generating set operates in parallel with the public supply (551.7)										N/A		No	
5.0	FINAL CIRCUITS													
5.1	Identification of conductors (514.3.1)										✓		No	
5.2	Cables correctly supported throughout their run (521.10.202; 522.8.5)										✓		No	
5.3	Condition of insulation of live parts (416.1)										✓		No	

CONDITION REPORT INSPECTION SCHEDULE FOR DOMESTIC AND SIMILAR PREMISES WITH UP TO 100A SUPPLY CONTINUED

Note: this form is suitable for many types of smaller installations not exclusively domestic.

Outcomes	Acceptable condition	✓	Unacceptable condition	State C1 or C2	Improvement recommended	State C3	Further investigation	FI	Not verified	N/V	Limitation	LIM	Not applicable	N/A
Item No	Description										Outcome			Comments
5.0	FINAL CIRCUITS (Continued)													
5.4	Non-sheathed cables protected by enclosure in conduit, ducting or trunking (521.10.1)										✓			No
5.4.1	To include the integrity of conduit and trunking systems (metallic and plastic)										✓			No
5.5	Adequacy of cables for current-carrying capacity with regard for the type and nature of installation (Section 523)										✓			No
5.6	Coordination between conductors and overload protective devices (433.1; 533.2.1)										✓			No
5.7	Adequacy of protective devices: type and rated current for fault protection (411.3)										✓			No
5.8	Presence and adequacy of circuit protective conductors (411.3.1; Section 543)										✓			No
5.9	Wiring system(s) appropriate for the type and nature of the installation and external influences (Section 522)										✓			No
5.10	Concealed cables installed in prescribed zones (see Section D. Extent and limitations) (522.6.202)										✓			No
5.11	Cables concealed under floors, above ceilings or in walls/partitions, adequately protected against damage (see Section D. Extent and limitations) (522.6.204)										✓			No
5.12	Provision of additional requirements for protection by RCD not exceeding 30 mA:													
5.12.1	For all socket-outlets of rating 32 A or less, unless an exception is permitted (411.3.3)										✓			No
5.12.2	For the supply of mobile equipment not exceeding 32 A rating for use outdoors (411.3.3)										✓			No
5.12.3	For cables concealed in walls at a depth of less than 50 mm (522.6.202; 522.6.203)										✓			No
5.12.4	For cables concealed in walls/partitions containing metal parts regardless of depth (522.6.203)										✓			No
5.12.5	Final circuits supplying luminaires within domestic (household) premises (411.3.4)										N/A			No
5.13	Provision of fire barriers, sealing arrangements and protection against thermal effects (Section 527)										✓			No
5.14	Band II cables segregated/separated from Band I cables (528.1)										✓			No
5.15	Cables segregated/separated from communications cabling (528.2)										✓			No
5.16	Cables segregated/separated from non-electrical services (528.3)										✓			No
5.17	Termination of cables at enclosures - indicate extent of sampling in Section D of the report (Section 526)													
5.17.1	Connections soundly made and under no undue strain (526.6)										✓			No
5.17.2	No basic insulation of a conductor visible outside enclosure (526.8)										✓			No
5.17.3	Connections of live conductors adequately enclosed (526.5)										✓			No
5.17.4	Adequately connected at point of entry to enclosure (glands, bushes etc.) (522.8.5)										✓			No
5.18	Condition of accessories including socket-outlets, switches and joint boxes (651.2(v))										✓			No
5.19	Suitability of accessories for external influences (512.2)										✓			No
5.20	Adequacy of working space/accessibility to equipment (132.12; 513.1)										✓			No
5.21	Single-pole switching or protective devices in line conductors only (132.14.1;530.3.3)										✓			No
6.0	LOCATION(S) CONTAINING A BATH OR SHOWER													
6.1	Additional protection for all low voltage (LV) circuits by RCD not exceeding 30 mA (701.411.3.3)										✓			No
6.2	Where used as a protective measure, requirements for SELV or PELV met (701.414.4.5)										N/A			No
6.3	Shaver sockets comply with BS EN 61558-2-5 formerly BS 3535 (701.512.3)										N/A			No
6.4	Presence of supplementary bonding conductors, unless not required by BS 7671:2018 (701.415.2)										✓			No
6.5	Low voltage (e.g. 230 volt) socket-outlets sited at least 3 m from zone 1 (701.512.3)										✓			No
6.6	Suitability of equipment for external influences for installed location in terms of IP rating (701.512.2)										✓			No
6.7	Suitability of accessories and controlgear etc. for a particular zone (701.512.3)										✓			No
6.8	Suitability of current-using equipment for particular position within the location (701.55)										✓			No
7.0	OTHER PART 7 SPECIAL INSTALLATIONS OR LOCATIONS													
7.1	List all other special installations or locations present, if any. (Record separately the results of particular inspections applied.)									Number of locations	0			No

Inspected By

Name: Jamie Paulton

Date: 11/12/2020

Signature:



Board Details																
TO BE COMPLETED IN EVERY CASE					ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION											
Location of Distribution Board		Ground floor Lecture room 1 (Havells)			Supply to distribution board is from: N/A					Associated RCD (if any)						
Distribution board designation		DB F			No of phases		N/A		Nominal Voltage		N/A V		BS(EN)		N/A	
					Overcurrent protective device for the distribution circuit					RCD No of Poles		N/A				
					Type BS(EN)		N/A		Rating		N/A A		RCD Rating		N/A mA	
Circuit Details																
Circuit number and phase	Circuit designation	Type of wiring	Reference method	No of points served	Circuit conductors csa		Max permitted disconnection times (s)	Overcurrent protective device					RCD		Maximum permitted Zs (Ω)	
					Live mm ²	cpc mm ²		BS(EN)	AFDD	Type	Rating (A)	Short circuit capacity (kA)	Operating current (Δn)			
1/S	Water heater room 13	A	E	1	2.5	1.5	0.4	61009 RCD/RCBO		C	16	10	30	1667		
2/S	MSCP supply	F	E	10	4	4	0.4	60898 MCB		C	16	10	N/A	1.09		
3/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
4/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
5/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
6/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
7/S	Lights rm 3 lecture 1	A	E	8	1.5	1.5	0.4	61009 RCD/RCBO		C	10	10	30	1667		
8/S	Lights rm 2 lecture 2	A	E	8	2.5	1.5	0.4	61009 RCD/RCBO		C	10	10	30	1667		
9/S	Lights rm 34 MRR (range)	D	B	8	2.5	1.5	0.4	61009 RCD/RCBO		C	10	10	30	1667		
10/S	Lights rm 23 drill hall	D	B	18	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
11/S	Lights 24/28	D	B	8	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
12/S	Lights rm 16 office	D	B	5	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
13/S	Lights rm 14/15 office	D	B	10	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
14/S	Lights rm 13/29 corridor/WC	D	B	6	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
15/S	Lights external	D	B	6	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
16/S	Lights external	D	B	4	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
17/S	Lights main entrance	D	B	6	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667		
18/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
19/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
20/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
21/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
22/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
23/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
24/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
Wiring Code																
A	B	C	D	E	F	G	H	O								
PVC/PVC cables	PVC cables in metallic conduit	PVC cables in non-metallic conduit	PVC cables in metallic trunking	PVC cables in non-metallic trunking	PVC/SWA cables	XLPE/SWA cables	Mineral insulated cables	Other								

Board Tests

TO BE COMPLETED IN EVERY CASE

Correct supply polarity confirmed

✓

Phase sequence confirmed (where appropriate)

N/A

Supplementary Conductors

✓

ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Zs

N/A

 Ω Ipfc

N/A

 kA

Operating times of associated RCD (if any) At IΔn

N/A

 ms

TEST INSTRUMENTS (SERIAL NUMBERS) USED

Earth fault loop impedance

225710

RCD

225710

Insulation resistance

225710

Multi-function

N/A

Continuity

225710

Other

N/A

Details of circuits and/or equipment vulnerable to damage when testing

None

Circuit Tests

Circuit number and phase	Circuit Impedances Ω					Insulation resistance					Polarity (✓)	Maximum measured earth fault loop impedance Ω	RCD		AFDD Test button operation	Remarks see continuation sheet
	Ring final circuits only (measure end to end)			All circuits (At least one column to be completed)		Test Voltage	Live/ Live MΩ	Live/ Neutral MΩ	Live/ Earth MΩ	Earth/ Neutral MΩ			Operating time at IΔn (ms)	Test button operation		
	r1 (Line)	rN (Neutral)	r2 (cpc)	(R1 + R2)	(R2)											
1/S	N/A	N/A	N/A	0.42	N/A	500	N/A	200	200	200	✓	0.57	27	✓		NO
2/S	N/A	N/A	N/A	0.23	N/A	500	N/A	200	200	200	✓	0.38	N/A	N/A		NO
3/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
4/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
5/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
6/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
7/S	N/A	N/A	N/A	0.35	N/A	500	N/A	Lim	200	200	✓	0.50	29	✓		NO
8/S	N/A	N/A	N/A	0.44	N/A	500	N/A	Lim	200	200	✓	0.59	29	✓		NO
9/S	N/A	N/A	N/A	1.36	N/A	500	N/A	Lim	200	200	✓	1.51	29	✓		NO
10/S	N/A	N/A	N/A	0.54	N/A	500	N/A	Lim	200	200	✓	0.69	29	✓		NO
11/S	N/A	N/A	N/A	0.57	N/A	500	N/A	Lim	200	200	✓	0.72	29	✓		NO
12/S	N/A	N/A	N/A	0.39	N/A	500	N/A	Lim	200	200	✓	0.54	28	✓		NO
13/S	N/A	N/A	N/A	0.42	N/A	500	N/A	Lim	200	200	✓	0.57	29	✓		NO
14/S	N/A	N/A	N/A	0.76	N/A	500	N/A	Lim	200	200	✓	0.91	27	✓		NO
15/S	N/A	N/A	N/A	1.06	N/A	500	N/A	Lim	200	200	✓	1.21	29	✓		NO
16/S	N/A	N/A	N/A	0.84	N/A	500	N/A	Lim	200	200	✓	0.99	29	✓		NO
17/S	N/A	N/A	N/A	0.30	N/A	500	N/A	Lim	200	200	✓	0.45	23	✓		NO
18/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
19/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
20/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
21/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
22/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
23/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
24/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-

Tested By

Signature

Position

Approved Electrician

Name

Jamie Paulton

Date of testing

30/11/2020

Copyright © Trimble 2018, FastTest Plus v2018.0.0, IJ Cannings & Son Ltd

Page 6 of 17

Board Details														
TO BE COMPLETED IN EVERY CASE					ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION									
Location of Distribution Board	Ground floor Lecture room 1 (Havells)				Supply to distribution board is from: N/A					Associated RCD (if any)				
Distribution board designation	DB F				No of phases: N/A Nominal Voltage: N/A V					BS(EN): N/A				
					Overcurrent protective device for the distribution circuit					RCD No of Poles: N/A				
					Type BS(EN): N/A Rating: N/A A					RCD Rating: N/A mA				
Circuit Details														
Circuit number and phase	Circuit designation	Type of wiring	Reference method	No of points served	Circuit conductors csa		Max permitted disconnection times (s)	Overcurrent protective device					RCD	Maximum permitted Zs (Ω)
					Live mm ²	cpc mm ²		BS(EN)	AFDD	Type	Rating (A)	Short circuit capacity (kA)		
25/S	Sub Mains(DB R)	F	C	1	25	25	5	60898 MCB		C	63	10	N/A	0.28
26/S	Sockets rm 3 lecture 1	D	B	10	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
27/S	Sockets rm 2 lecture 2	D	B	8	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
28/S	Sockets MRR	D	B	5	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
29/S	Sockets rm 23 Drill hall	D	B	5	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
30/S	Sockets boiler room/stores	D	B	8	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
31/S	Fire alarm	D	B	1	2.5	1.5	0.4	60898 MCB		B	16	10	N/A	2.18
32/S	Power gate supply	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667
33/S	ICT cab supply	F	C	1	2.5	1.5	0.4	60898 MCB		C	16	10	N/A	1.09
34/S	Sockets rm 16 office	D	B	6	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
35/S	Sockets rm 15 office	D	B	6	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
36/S	Sockets rm 14 office	D	B	6	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667
37/S	Intruder alarm	D	B	1	2.5	1.5	0.4	60898 MCB		B	16	10	N/A	2.18
38/S	Sockets CCTV	D	B	4	2.5	1.5	0.4	61009 RCD/RCBO		B	20	10	30	1667
39/S	Hand dryer male WC	C	B	1	2.5	1.5	0.4	61009 RCD/RCBO		C	16	10	30	1667
40/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
41/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
42/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
43/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
44/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
45/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
46/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
47/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
48/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-
Wiring Code														
A	B	C	D	E	F	G	H	O						
PVC/PVC cables	PVC cables in metallic conduit	PVC cables in non-metallic conduit	PVC cables in metallic trunking	PVC cables in non-metallic trunking	PVC/SWA cables	XLPE/SWA cables	Mineral insulated cables	Other						

Board Tests

TO BE COMPLETED IN EVERY CASE

Correct supply polarity confirmed

✓

Phase sequence confirmed (where appropriate)

N/A

Supplementary Conductors

✓

ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Zs

N/A

ΩIpfdiv>N/A

kA

Operating times of associated RCD (if any) At IΔn

N/A

ms

TEST INSTRUMENTS (SERIAL NUMBERS) USED

Earth fault loop impedance

225710

RCD

225710

Insulation resistance

225710

Multi-function

N/A

Continuity

225710

Other

N/A

Details of circuits and/or equipment vulnerable to damage when testing

None

Circuit Tests

Circuit number and phase	Circuit Impedances Ω					Insulation resistance					Polarity (✓)	Maximum measured earth fault loop impedance Ω	RCD		AFDD Test button operation	Remarks see continuation sheet
	Ring final circuits only (measure end to end)			All circuits (At least one column to be completed)		Test Voltage	Live/ Live MΩ	Live/ Neutral MΩ	Live/ Earth MΩ	Earth/ Neutral MΩ			Operating time at IΔn (ms)	Test button operation		
	r1 (Line)	rN (Neutral)	r2 (cpc)	(R1 + R2)	(R2)											
25/S	N/A	N/A	N/A	0.06	N/A	500	N/A	200	200	200	✓	0.21	N/A	N/A		NO
26/S	0.38	0.38	0.63	0.38	N/A	500	N/A	200	200	200	✓	0.53	28	✓		NO
27/S	0.33	0.33	0.55	0.16	N/A	500	N/A	200	200	200	✓	0.31	23	✓		NO
28/S	0.79	0.79	1.31	0.12	N/A	500	N/A	200	200	200	✓	0.27	29	✓		NO
29/S	0.75	0.75	1.25	0.19	N/A	500	N/A	200	200	200	✓	0.34	29	✓		NO
30/S	0.99	1.00	1.65	0.34	N/A	500	N/A	200	200	200	✓	0.49	28	✓		NO
31/S	N/A	N/A	N/A	0.35	N/A	500	N/A	200	200	200	✓	0.50	N/A	N/A		NO
32/S	N/A	N/A	N/A	0.41	N/A	500	N/A	200	200	200	✓	0.56	29	✓		NO
33/S	N/A	N/A	N/A	0.36	N/A	500	N/A	200	200	200	✓	0.51	N/A	N/A		NO
34/S	0.50	0.50	0.83	0.42	N/A	500	N/A	200	200	200	✓	0.57	29	✓		NO
35/S	0.58	0.58	0.96	0.40	N/A	500	N/A	200	200	200	✓	0.55	25	✓		NO
36/S	0.71	0.70	1.16	0.41	N/A	500	N/A	200	200	200	✓	0.56	34	✓		NO
37/S	N/A	N/A	N/A	0.27	N/A	500	N/A	200	200	200	✓	0.42	N/A	N/A		NO
38/S	N/A	N/A	N/A	0.31	N/A	500	N/A	200	200	200	✓	0.46	29	✓		NO
39/S	N/A	N/A	N/A	0.42	N/A	500	N/A	200	200	200	✓	0.57	Fail	✓		NO
40/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
41/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
42/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
43/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
44/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
45/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
46/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
47/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
48/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-

Tested By

Signature

Position

Approved Electrician

Name

Jamie Paulton

Date of testing

30/11/2020

Copyright © Trimble 2018, FastTest Plus v2018.0.0, IJ Cannings & Son Ltd

Page 8 of 17

Board Details		
TO BE COMPLETED IN EVERY CASE		ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION
Location of Distribution Board	Ground floor Lecture room 1 (Havells)	<div>Supply to distribution board is from: N/A</div> <div>No of phases: N/A Nominal Voltage: N/A V</div> <div>Overcurrent protective device for the distribution circuit</div> <div>Type BS(EN): N/A Rating: N/A A</div> <div>Associated RCD (if any)</div> <div>BS(EN): N/A</div> <div>RCD No of Poles: N/A</div> <div>RCD Rating: N/A mA</div>
Distribution board designation	DB F	

[illegible]

A	B	C	D	E	F	G	H	O
PVC/PVC cables	PVC cables in metallic conduit	PVC cables in non-metallic conduit	PVC cables in metallic trunking	PVC cables in non-metallic trunking	PVC/SWA cables	XLPE/SWA cables	Mineral insulated cables	Other

TO BE COMPLETED IN EVERY CASE		TEST INSTRUMENTS (SERIAL NUMBERS) USED			
Correct supply polarity confirmed	<input checked="" type="checkbox"/>			Phase sequence confirmed (where appropriate)	<input type="text" value="N/A"/>
Supplementary Conductors	<input checked="" type="checkbox"/>				
ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION					
Zs	<input type="text" value="N/A"/>	Ω	Ipf	<input type="text" value="N/A"/>	kA
Operating times of associated RCD (if any) At		$I \Delta n$	<input type="text" value="N/A"/>	ms	
Earth fault loop impedance		<input type="text" value="225710"/>	RCD	<input type="text" value="225710"/>	
Insulation resistance		<input type="text" value="225710"/>	Multi-function	<input type="text" value="N/A"/>	
Continuity		<input type="text" value="225710"/>	Other	<input type="text" value="N/A"/>	

Details of circuits and/or equipment vulnerable to damage when testing

None

Circuit Tests

[illegible]

Tested By _____

Signature		Position	Approved Electrician
-----------	---	----------	----------------------

Position	Approved Electrician
----------	----------------------


Name: Jamie Paulton

Date of testing 30/11/2020


Board Details		
TO BE COMPLETED IN EVERY CASE		ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION
Location of Distribution Board	Kitchen (Havells)	Supply to distribution board is from: SubMains(DB F, 25/S)
Distribution board designation	DB R	No of phases 1 Nominal Voltage 230 V
		Overcurrent protective device for the distribution circuit
		Type BS(EN) 60898 MCB C Rating 63 A
		Associated RCD (if any)
		BS(EN) N/A
		RCD No of Poles N/A
		RCD Rating N/A mA

Circuit Details															
Circuit number and phase	Circuit designation	Type of wiring	Reference method	No of points served	Circuit conductors csa		Max permitted disconnection times (s)	Overcurrent protective device					RCD	Maximum permitted Zs (Ω)	
					Live mm ²	cpc mm ²		BS(EN)	AFDD	Type	Rating (A)	Short circuit capacity (kA)	Operating current (Δn)		
1/S	Water heater rm 4 servery	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		C	16	10	30	1667	
2/S	Water heater rm 5 male WC	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		C	16	10	30	1667	
3/S	Water heater rm 6 female WC	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		C	16	10	30	1667	
4/S	Water heater rm 7 male WC	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		C	16	10	30	1667	
5/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
6/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
7/S	Lights rm 4 & 5 servery,WC	D	B	8	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
8/S	Lights rm 6,7,33 Femal & male WC	D	B	10	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
9/S	Lights ground floor corridor	D	B	8	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
10/S	Lights 1,8,9 armoury & ammo bunker	D	B	10	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
11/S	Lights rm 30 rear stairs	D	B	9	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
12/S	Lights rm 17 canteen	D	B	17	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
13/S	Lights rm 18,20 office	D	B	9	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
14/S	Lights 21,22,31,32 offices	D	B	8	1.5	1	0.4	61009 RCD/RCBO		C	10	10	30	1667	
15/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
16/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
17/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
18/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
19/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
20/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
21/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
22/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
23/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	
24/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-	

Wiring Code								
A	B	C	D	E	F	G	H	O
PVC/PVC cables	PVC cables in metallic conduit	PVC cables in non-metallic conduit	PVC cables in metallic trunking	PVC cables in non-metallic trunking	PVC/SWA cables	XLPE/SWA cables	Mineral insulated cables	Other

Board Tests																						
TO BE COMPLETED IN EVERY CASE											TEST INSTRUMENTS (SERIAL NUMBERS) USED											
Correct supply polarity confirmed		<input checked="" type="checkbox"/>		Phase sequence confirmed (where appropriate)		N/A					Earth fault loop impedance		225710		RCD		225710					
Supplementary Conductors		<input checked="" type="checkbox"/>													Insulation resistance		225710		Multi-function		N/A	
ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION																						
Zs		0.21		Ω		Ipf		1.87		kA		Continuity		225710		Other		N/A				
Operating times of associated RCD (if any) At $I\Delta n$ N/A ms																						
Details of circuits and/or equipment vulnerable to damage when testing																						
None																						
Circuit Tests																						
Circuit number and phase	Circuit Impedances Ω					Insulation resistance					Polarity (\vee)	Maximum measured earth fault loop impedance Ω	RCD		AFDD Test button operation	Remarks see continuation sheet						
	Ring final circuits only (measure end to end)			All circuits (At least one column to be completed)		Test Voltage	Live/ Live $M\Omega$	Live/ Neutral $M\Omega$	Live/ Earth $M\Omega$	Earth/ Neutral $M\Omega$			Operating time at $I\Delta n$ (ms)	Test button operation								
	r ₁ (Line)	r _n (Neutral)	r ₂ (cpc)	(R ₁ + R ₂)	(R ₂)																	
1/S	N/A	N/A	N/A	0.19	N/A	500	N/A	200	200	200	\checkmark	0.40	28	\checkmark		NO						
2/S	N/A	N/A	N/A	0.28	N/A	500	N/A	200	200	200	\checkmark	0.49	29	\checkmark		NO						
3/S	N/A	N/A	N/A	0.28	N/A	500	N/A	200	200	200	\checkmark	0.49	29	\checkmark		NO						
4/S	N/A	N/A	N/A	0.29	N/A	500	N/A	200	200	200	\checkmark	0.50	29	\checkmark		NO						
5/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
6/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
7/S	N/A	N/A	N/A	0.28	N/A	500	N/A	Lim	200	200	\checkmark	0.49	28	\checkmark		NO						
8/S	N/A	N/A	N/A	0.51	N/A	500	N/A	Lim	200	200	\checkmark	0.72	24	\checkmark		NO						
9/S	N/A	N/A	N/A	0.61	N/A	500	N/A	Lim	200	200	\checkmark	0.82	29	\checkmark		NO						
10/S	N/A	N/A	N/A	0.64	N/A	500	N/A	Lim	200	200	\checkmark	0.85	28	\checkmark		NO						
11/S	N/A	N/A	N/A	0.68	N/A	500	N/A	Lim	200	200	\checkmark	0.89	28	\checkmark		NO						
12/S	N/A	N/A	N/A	0.39	N/A	500	N/A	Lim	200	200	\checkmark	0.60	28	\checkmark		NO						
13/S	N/A	N/A	N/A	0.56	N/A	500	N/A	Lim	200	200	\checkmark	0.77	30	\checkmark		NO						
14/S	N/A	N/A	N/A	0.71	N/A	500	N/A	Lim	200	200	\checkmark	0.92	29	\checkmark		NO						
15/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
16/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
17/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
18/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
19/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
20/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
21/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
22/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
23/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
24/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-						
Tested By																						
Signature							Position		Approved Electrician													
Name		Jamie Paulton					Date of testing		30/11/2020													

Board Details																
TO BE COMPLETED IN EVERY CASE					ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION											
Location of Distribution Board		Kitchen (Havells)			Supply to distribution board is from: SubMains(DB F, 25/S)					Associated RCD (if any)						
Distribution board designation		DB R			No of phases		1		Nominal Voltage		230 V		BS(EN)		N/A	
					Overcurrent protective device for the distribution circuit					RCD No of Poles		N/A				
					Type BS(EN)		60898 MCB C		Rating		63 A		RCD Rating		N/A mA	
Circuit Details																
Circuit number and phase	Circuit designation	Type of wiring	Reference method	No of points served	Circuit conductors csa		Max permitted disconnection times (s)	Overcurrent protective device					RCD	Maximum permitted Zs (Ω)		
					Live mm ²	cpc mm ²		BS(EN)	AFDD	Type	Rating (A)	Short circuit capacity (kA)			Operating current (ΔIn)	
25/S	Sockets rm 4 servery	D	B	10	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
26/S	Hand dryer rm 5 WC	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667		
27/S	Hand dryer rm 5a disabled WC	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667		
28/S	Hand dryer rm 4 female WC	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667		
29/S	Hand dryer rm 7 male WC	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667		
30/S	Sockets ground floor corridor	D	B	3	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
31/S	Sockets armoury	D	B	3	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
32/S	Sockets rm 1 gym/main store	D	B	4	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
33/S	Intruder alarm armoury	O	B	1	2.5	1.5	0.4	60898 MCB		B	16	10	N/A	2.18		
34/S	Disabled alarm	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667		
35/S	Sockets behind bar	D	B	4	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
36/S	Sockets rm 17 lecture	D	B	6	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
37/S	Sockets rm 18 & 19 office	D	B	7	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
38/S	Sockets rm 20,21 office	D	B	10	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
39/S	Sockets rm 22,31 office	D	B	10	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
40/S	Sockets rm 32 office	D	B	8	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
41/S	Sockets cleaners 1st floor near side	D	B	6	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
42/S	Sockets cleaners 1st floor far side	D	B	6	2.5	1.5	0.4	61009 RCD/RCBO		C	32	10	30	1667		
43/S	Shower male WC	D	B	1	10	4	0.4	61009 RCD/RCBO		B	50	10	30	1667		
44/S	Shower female WC	D	B	1	10	4	0.4	61009 RCD/RCBO		B	50	10	30	1667		
45/S	Shower rm 7 male WC	D	B	1	10	4	0.4	61009 RCD/RCBO		B	50	10	30	1667		
46/S	TV amp 1st floor	C	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667		
47/S	Intruder alarm 1st floor	D	B	1	2.5	1.5	0.4	61009 RCD/RCBO		B	16	10	30	1667		
48/S	SPARE	-	-	-	-	-	-	-	-	-	-	-	-	-		
Wiring Code																
A	B	C	D	E	F	G	H	O								
PVC/PVC cables	PVC cables in metallic conduit	PVC cables in non-metallic conduit	PVC cables in metallic trunking	PVC cables in non-metallic trunking	PVC/SWA cables	XLPE/SWA cables	Mineral insulated cables	Other								

Board Tests																
TO BE COMPLETED IN EVERY CASE											TEST INSTRUMENTS (SERIAL NUMBERS) USED					
Correct supply polarity confirmed <input checked="" type="checkbox"/>					Phase sequence confirmed (where appropriate) <input type="text" value="N/A"/>						Earth fault loop impedance <input type="text" value="225710"/> RCD <input type="text" value="225710"/> Insulation resistance <input type="text" value="225710"/> Multi-function <input type="text" value="N/A"/> Continuity <input type="text" value="225710"/> Other <input type="text" value="N/A"/>					
Supplementary Conductors <input checked="" type="checkbox"/>																
ONLY TO BE COMPLETED IF THE DISTRIBUTION BOARD IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION																
Zs <input type="text" value="0.21"/> Ω Ip <input type="text" value="1.87"/> kA																
Operating times of associated RCD (if any) At I Δ n <input type="text" value="N/A"/> ms																
Details of circuits and/or equipment vulnerable to damage when testing																
<div>None</div>																
Circuit Tests																
Circuit number and phase	Circuit Impedances Ω					Insulation resistance					Polarity (✓)	Maximum measured earth fault loop impedance Ω	RCD		AFDD Test button operation	Remarks see continuation sheet
	Ring final circuits only (measure end to end)			All circuits (At least one column to be completed)		Test Voltage	Live/Live MΩ	Live/Neutral MΩ	Live/Earth MΩ	Earth/Neutral MΩ			Operating time at I Δ n (ms)	Test button operation		
	r ₁ (Line)	r _n (Neutral)	r ₂ (cpc)	(R ₁ + R ₂)	(R ₂)											
25/S	0.31	0.31	0.50	0.15	N/A	500	N/A	200	200	200	✓	0.36	29	✓		NO
26/S	N/A	N/A	N/A	0.40	N/A	500	N/A	200	200	200	✓	0.61	29	✓		NO
27/S	N/A	N/A	N/A	0.42	N/A	500	N/A	200	200	200	✓	0.63	27	✓		NO
28/S	N/A	N/A	N/A	0.38	N/A	500	N/A	200	200	200	✓	0.59	29	✓		NO
29/S	N/A	N/A	N/A	0.30	N/A	500	N/A	200	200	200	✓	0.51	29	✓		NO
30/S	0.38	0.38	0.63	0.06	N/A	500	N/A	200	200	200	✓	0.27	29	✓		NO
31/S	0.35	0.36	0.57	0.21	N/A	500	N/A	200	200	200	✓	0.42	29	✓		NO
32/S	0.81	0.79	1.31	0.48	N/A	500	N/A	200	200	200	✓	0.69	28	✓		NO
33/S	N/A	N/A	N/A	0.32	N/A	500	N/A	200	200	200	✓	0.53	N/A	N/A		NO
34/S	N/A	N/A	N/A	0.23	N/A	500	N/A	200	200	200	✓	0.44	32	✓		NO
35/S	0.41	0.40	0.66	0.21	N/A	500	N/A	200	200	200	✓	0.42	29	✓		NO
36/S	0.59	0.58	0.96	0.27	N/A	500	N/A	200	200	200	✓	0.48	29	✓		NO
37/S	0.49	0.48	0.80	0.26	N/A	500	N/A	200	200	200	✓	0.47	29	✓		NO
38/S	0.65	0.65	1.07	0.48	N/A	500	N/A	200	200	200	✓	0.69	30	✓		NO
39/S	0.73	0.73	1.21	0.40	N/A	500	N/A	200	200	200	✓	0.61	29	✓		NO
40/S	0.55	0.55	0.91	0.28	N/A	500	N/A	200	200	200	✓	0.49	27	✓		NO
41/S	0.69	0.69	1.15	0.19	N/A	500	N/A	200	200	200	✓	0.40	28	✓		NO
42/S	0.70	0.71	1.16	0.25	N/A	500	N/A	200	200	200	✓	0.46	29	✓		NO
43/S	N/A	N/A	N/A	0.38	N/A	500	N/A	200	200	200	✓	0.59	29	✓		NO
44/S	N/A	N/A	N/A	0.22	N/A	500	N/A	200	200	200	✓	0.43	24	✓		NO
45/S	N/A	N/A	N/A	0.14	N/A	500	N/A	200	200	200	✓	0.35	29	✓		NO
46/S	N/A	N/A	N/A	0.29	N/A	500	N/A	200	200	200	✓	0.50	27	✓		NO
47/S	N/A	N/A	N/A	0.30	N/A	500	N/A	200	200	200	✓	0.51	24	✓		NO
48/S	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Tested By																
Signature							Position		Approved Electrician							
Name		Jamie Paulton					Date of testing		30/11/2020							

Board Tests

TO BE COMPLETED IN EVERY CASE

Phase sequence confirmed (where appropriate) N/A

(where appropriate)

μ	0.01	σ	1.07
-------	------	----------	------

Operating times of associated RCD (if any) At I Δ n	N/A	ms
--	-----	----

TEST INSTRUMENTS (SERIAL NUMBERS) USED	
1	
2	
3	
4	
5	
6	
7	
8	
9	
10	
11	
12	
13	
14	
15	
16	
17	
18	
19	
20	
21	
22	
23	
24	
25	
26	
27	
28	
29	
30	
31	
32	
33	
34	
35	
36	
37	
38	
39	
40	
41	
42	
43	
44	
45	
46	
47	
48	
49	
50	
51	
52	
53	
54	
55	
56	
57	
58	
59	
60	
61	
62	
63	
64	
65	
66	
67	
68	
69	
70	
71	
72	
73	
74	
75	
76	
77	
78	
79	
80	
81	
82	
83	
84	
85	
86	
87	
88	
89	
90	
91	
92	
93	
94	
95	
96	
97	
98	
99	
100	

225710

N/A

N/A

[illegible]

None

	Circuit Impedances	Insulation resistance			RCD	5	
--	--------------------	-----------------------	--	--	-----	---	--

[illegible]

I. B. Lutz

Approved Electrician

Jamie Paulton

30/11/2020

Item No	Description	Code
	boards containing many spare ways(42 spare ways in total) for future additional circuits to be added. May be best suited for a 3 phase supply for this installation to spread loads accordingly.	
3	Found many RCBOs & MCBs within both DB F & DB R with poor terminations. The heads of termination screw has been rounded off, so very difficult to disconnect/reconnect for testing purposes. Found 32A 30mA RCBOs for ring circuits to be the worst. Very poor considering installation is only estimated to be about 5/6 years old. May need replacing in near future to get correct torque setting on connections.(2 Nm for Havells)	C3
4	Outside light with water ingress in car park area. (round bulkhead with white base)	C2
5	Found most light switches throughout with no brown sleeving on the switch line to identify it as live.	C3
6	DB F- cct 14 MK retractive 3 position switch damaged in room 14 office 1st floor.	C2
7	DB F- cct 36 found faulty 30mA RCBO thread had gone on live termination, couldnt tighten connection. Had to temporarily replace C32 30mA RCBO (hager) Requires changing for havells RCBO	C2
8	DB F- cct 39 C16 30mA RCBO failed to operate under fault conditions.	C2
9	DB R- ccts 51 & 53 both Hager B16 30mA RCBOs wrong type should be Havells.	C2

Code Key

C1 - Danger present. Risk of injury. Immediate remedial action required

C2 - Potentially dangerous - urgent remedial action required

C3 - Improvement recommended

FI - Further investigation required without delay

CONDITION REPORT GUIDANCE FOR RECIPIENTS (to be appended to the Report)

This Report is an important and valuable document which should be retained for future reference.

1. The purpose of this Report is to confirm, so far as reasonably practicable, whether or not the electrical installation is in a satisfactory condition for continued service (see Section E). The Report should identify any damage, deterioration, defects and/or conditions which may give rise to danger (see Section K).
2. The person ordering the Report should have received the 'original' Report and the inspector should have retained a duplicate.
3. The 'original' Report should be retained in a safe place and be made available to any person inspecting or undertaking work on the electrical installation in the future. If the property is vacated, this Report will provide the new owner/occupier with details of the condition of the electrical installation at the time the Report was issued.
4. Where the installation incorporates a residual current device (RCD) there should be a notice at or near the device stating that it should be tested six-monthly. **For safety reasons it is important that this instruction is followed.**
5. Section D (Extent and Limitations) should identify fully the extent of the installation covered by this Report and any limitations on the inspection and testing. The inspector should have agreed these aspects with the person ordering the Report and with other interested parties (licensing authority, insurance company, mortgage provider and the like) before the inspection was carried out.
6. Some operational limitations such as inability to gain access to parts of the installation or an item of equipment may have been encountered during the inspection. The inspector should have noted these in Section D.
7. For items classified in Section K as C1 ('Danger present'), **the safety of those using the installation is at risk**, and it is recommended that a skilled person or persons competent in electrical installation work undertakes the necessary remedial work immediately.
8. For items classified in Section K as C2 ('Potentially dangerous'), **the safety of those using the installation may be at risk** and it is recommended that a skilled person or persons competent in electrical installation work undertakes the necessary remedial work as a matter of urgency.
9. Where it has been stated in Section K that an observation requires further investigation (code FI) the inspection has revealed an apparent deficiency which may result in a code C1 or C2, and could not, due to the extent or limitations of the inspection, be fully identified. Such observations should be investigated without delay. A further examination of the installation will be necessary, to determine the nature and extent of the apparent deficiency (see Section F).
10. For safety reasons, the electrical installation should be re-inspected at appropriate intervals by a skilled person or persons, competent in such work. The recommended date by which the next inspection is due is stated in Section F of the Report under 'Recommendations' and on a label at or near to the consumer unit/distribution board.