

PART 1 : DETAILS OF THE CONTRACTOR, CLIENT AND INSTALLATION

DETAILS OF THE CONTRACTOR		DETAILS OF THE CLIENT		DETAILS OF THE INSTALLATION	
Registration No. 028288000	Branch No. 000	Contractor Reference Number (CRN) 23504	Occupier 2391 (Parkstone) Squadron	Address: Herbert Avenue, Poole, Dorset	Postcode: BH12 4HN
Trading Title: R J Electrical Services Ltd		Name: Wessex RFCA			
Address: Unit 3a, Barnack Industrial Esta, Kingsway, Salisbury		Address: Wessex Reserve Forces & Cadets Association, Mount House, Mount Street, TAUNTON, Somerset			
Postcode: SP2 0AW	Tel No. 01722741091	Postcode: TA1 3QE	Tel No. N/A		
				Postcode: BH12 4HN	Tel No. N/A

PART 2 : PURPOSE OF THE REPORT

Purpose for which this report is required: Scheduled 5 yearly inspection

Date(s) when inspection and testing was carried out: 26/07/2022

Records available: (X)

Previous inspection report available: (✓)

Previous report date: (09/11/2017)

PART 3 : SUMMARY OF THE CONDITION OF THE INSTALLATION

General condition of the installation (in terms of electrical safety):

Generally good with recommendations. See attached continuation page for details.

Estimated age of electrical installation: (30) Years

Evidence of additions or alterations: (✓)

Overall assessment of the installation is: **Satisfactory/Unsatisfactory* (delete as appropriate)**

PART 4 : DECLARATION

INSPECTION AND TESTING

I, being the person responsible for the inspection and testing of the electrical installation, particulars of which are described in PART 7, having exercised reasonable skill and care when carrying out the inspection and testing of the existing installation, hereby CERTIFY that the information in this report, including the observations (page 2) and the attached schedules, provides an accurate assessment of the condition of the electrical installation taking into account the stated extent of the installation and the limitations on the inspection and testing.

Name (capital): BRIAN MCCARTHY

Signature: (Signature)

Date: 27/07/2022

REVIEWED BY THE REGISTERED QUALIFIED SUPERVISOR FOR THE APPROVED CONTRACTOR

Name (capital): ROBERT COOMBS

Signature: (Signature)

Date: 27/07/2022

*An unsatisfactory assessment indicates that dangerous (CODE C1) and/or potentially dangerous (CODE C2) conditions have been identified in PART 6, or that Further Investigation (CODE F1) without delay is required.

PART 5: NEXT INSPECTION

I/We (as indicated on page 1) recommend, subject to the necessary remedial work being taken, this installation should be further inspected and tested after an interval of not more than 5 years/~~months~~* (delete as appropriate)

Give reason for recommendation: Age, condition & type of usage.

PART 6: OBSERVATIONS AND RECOMMENDATIONS FOR ACTIONS TO BE TAKEN

CODES: *One of the following Codes, as appropriate, has been allocated to each of the observations made below to indicate to the person(s) responsible for the electrical installation the degree of urgency for remedial action*

CODE C1 'Danger Present'
Immediate remedial action required

CODE C2 Potentially Dangerous
Urgent remedial action required

CODE C3
Improvement Recommended

CODE H
'Further Investigation Required'

Referring to the Schedule of Items Inspected (see PART 10), the attached Schedule of Circuit Details and Test Results (see PART 12), and subject to any agreed limitations listed in PART 7,

There are no items adversely affecting electrical safety (.....), OR The following observations and recommendations for action are made:

Observation(s)

1	5	13	limited provision of RCD's for fault protection	(C3)	(General)
---	---	----	---	------	-----------

2) 5.14 Limited provision of RCD's for additional protection (C3) (General)

3	1	5.15	limited provision of RCD's for protection against fire.	(C3...)	(General)
---	---	------	---	---------	-----------

6.18 a) General lack of 30mA RCD protection to the majority of socket outlets.

5) (6.18 b) RCD socket adjacent to the entrance door must be used for any equipment outside. (C3) (Outside usage)

[illegible][illegible][illegible]

.....

.....

.....

.....

Additional names?	None	State name numbers	N/A

Item	Improvement recommended for items:	NA
1	1,2,3,4,5	
2		
3		
4		
5		
6		
7		
8		
9		
10		
11		
12		
13		
14		
15		
16		
17		
18		
19		
20		
21		
22		
23		
24		
25		
26		
27		
28		
29		
30		
31		
32		
33		
34		
35		
36		
37		
38		
39		
40		
41		
42		
43		
44		
45		
46		
47		
48		
49		
50		
51		
52		
53		
54		
55		
56		
57		
58		
59		
60		
61		
62		
63		
64		
65		
66		
67		
68		
69		
70		
71		
72		
73		
74		
75		
76		
77		
78		
79		
80		
81		
82		
83		
84		
85		
86		
87		
88		
89		
90		
91		
92		
93		
94		
95		
96		
97		
98		
99		
100		

Urgent remedial action required for items: (N/A)

Further investigation required for items: (N/A)

**The proposed date for the next inspection should take into consideration any legislative or licensing requirements and the frequency and quality of maintenance that the installation can reasonably be expected to receive during its intended life. The period should be agreed between relevant parties.*

PART 7 : DETAILS AND LIMITATIONS OF THE INSPECTION AND TESTING

The inspection and testing has been carried out in accordance with BS 7671: 2018, as amended. Cables concealed within trunking and conduits, or cables and conduits concealed under floors, in inaccessible roof spaces and generally within the fabric of the building or underground, have not been visually inspected unless specifically agreed between the Client and the Inspector prior to inspection.

Details of the installation covered by this report: Fixed wiring only

Agreed limitations including the reasons, if any, on the inspection and testing: None (see additional page No. N/A)

Extent of sampling: 20% of accessories were removed for testing & visual inspection. (see additional page No. N/A)

Operational limitations including the reasons: Could not confirm presence of fire barriers or segregation of circuitry. Restricted access trunking/conduits. (see additional page No. N/A)

PART 8 : SUPPLY CHARACTERISTICS AND EARTHING ARRANGEMENTS

System type and earthing arrangements	Number and type of live conductors	Nature of supply parameters
TN-C-S: (✓) TN-S: (N/A) TT: (N/A)	AC 1-phase, 2-wire: (N/A) 2-phase, 3-wire: (N/A) 3-phase, 3-wire: (N/A) 3-phase, 4-wire: (✓)	Nominal line voltage, $U^{(1)}$: (400) V Nominal line voltage to Earth, $U_0^{(1)}$: (230) V Nominal frequency, $f^{(1)}$: (50) Hz Prospective fault current, $I_{pf}^{(1)*}$: (1.07) kA External loop impedance, $Z_e^{(1)*}$: (0.21) Ω
Other (state): N/A	DC 2-wire: (N/A) 3-wire: (N/A) Other: (N/A)	
Supply protective device (BS EN) 1361	Confirmation of supply polarity: (✓)	
Type: (II)	Rated current: (100) A	
	Other sources of supply (as detailed on attached schedule)	Page No: (N/A)

PART 9 : PARTICULARS OF INSTALLATION REFERRED TO IN THIS REPORT

Means of Earthing	Main protective conductors	Main protective bonding connections	Main switch / Switch-fuse / Circuit-breaker / RCD
Distributor's facility: (✓) Installation earth electrode: (N/A)	Earthing conductor: (material) Copper (csa) 16 mm ² Connection / continuity verified: (✓)	Water installation pipes: (✓) Gas installation pipes: (N/A) Structural steel: (N/A) Oil installation pipes: (N/A) Lightning protection: (N/A) Other (state): (N/A)	Type: (BS (EN) 5419) Location: (Cupboard in Drill Hall) No. of poles: (3) Current rating: (100) A Rating / setting of device: (N/A) A (400) V Voltage rating: (N/A) V
Where an earth electrode is used insert Type – rod(s), tape, etc: (None) Location: (N/A) Electrode resistance to Earth: (N/A) Ω	Main protective bonding conductors: (material) Copper (csa) 16 mm ² Connection / continuity verified: (✓)		Where an RCD is used as the main switch RCD rated residual operating current, $I_{\Delta n}$: (N/A) mA Measured operating time: (N/A) ms Rated time delay: (N/A) ms

*Where the installation is supplied by more than one source, the higher or highest values of prospective fault current, I_{pf} , and external earth fault loop impedance, Z_e , must be recorded.

All fields must be completed. Enter either, as appropriate: '✓' if Acceptable condition; 'N/A' if Not applicable; 'LIM' if a Limitation exists.

or Code appropriately – CODE 'C1', 'C2', 'C3' or 'F' (codes to be recorded in PART 6, with additional comments (where appropriate) on attached numbered sheets)

PART 10: SCHEDULE OF ITEMS INSPECTED

1. External condition of electrical intake equipment (visual inspection only)
(If inadequacies are identified with the intake equipment, it is recommended the person ordering the report informs the appropriate authority.)

4. Other methods of protection

Page No. (N/A)
(N/A)
N/A

5.2.4 Single-pole switching or protective devices in line conductors only: (.....✓)

5.25 Protection against mechanical damage where cables enter equipment:

5.26 Protection against electromagnetic effects where cables enter ferromagnetic enclosures:

6. Distribution / final circuits

6.1 Identification of conductors:

6.2 Cables correctly supported throughout their length:

6.3 Condition of insulation of live parts:

6.4 Non-sheathed cables protected by enclosures in conduit, ducting or trunking:

6.5 Suitability of containment systems for continued use (including flexible conduit):

6.6 Cables correctly terminated in enclosures

(indicate extent of sampling in PART 7 of report):

6.7 Indication of SPD(s) continued functionality confirmed:

6.8 Adequacy of AFDD(s), where specified:

6.9 Confirmation that conductor connections, including connections to busbars are correctly located in terminals

and are tight and secure:

6.10 Examination of cables for signs of unacceptable thermal and mechanical damage / deterioration:

6.1.1 Adequacy of cables for current-carrying capacity with regard

to the type and nature of installation.

6.1.12 Adequacy of protective devices; type and rated current for fault protection:

6.13 Presence and adequacy of circuit protective conductors:

6.14 Co-ordination between conductors and overload protective devices:

6.1.5 Cable installation methods / practices appropriate to the type and nature of installation and external influences:

6.16 Cables where exposed to direct sunlight, or a suitable type of adequately protected against solar radiation:

6.1/ Cables adequately protected against damage and abrasion:

All fields must be completed.

Enter either, as appropriate: '✓' if Acceptable condition;

'N/A' if Not applicable;

'LIM' if a Limitation exists;

or Code appropriately – CODE 'C1', 'C2', 'C3' or 'FI' (codes to be recorded in PART 6,

numbered sheets/

PART 10 : SCHEDULE OF ITEMS INSPECTED

6.18 Provision of additional protection by an RCD not exceeding 30 mA	(.....)	6.26 Single-pole switching or protective devices in line conductors only:	(.....)	8. Current-using equipment (<i>permanently connected</i>)	(.....)
a) For all socket-outlets with a rated current not exceeding 32 A, unless exempt:	(C3.....)	6.27 Adequacy of connections, including CPCs, within accessories and to fixed and stationary equipment:	(.....)	8.1 Condition of equipment in terms of IP rating:	(.....)
b) Supplies for mobile equipment with a rated current not exceeding 32 A for use outdoors:	(C3.....)			8.2 Equipment does not constitute a fire hazard:	(.....)
c) For cables concealed in walls / partitions at a depth of less than 50 mm:	(N/A.....)			8.3 Enclosure not damaged / deteriorated so as to impair safety:	(.....)
d) For cables concealed in walls / partitions containing metal parts regardless of depth:	(N/A.....)			8.4 Suitability for the environment and external influences:	(.....)
e) Circuits supplying luminaires within domestic (household) premises:	(N/A.....)			8.5 Security of fixing:	(.....)
Note: Older installations designed prior to BS 7671: 2018 may not have been provided with RCDs for additional protection.					
6.19 Provision of fire barriers, sealing arrangements and protection against thermal effects:	(LIM.....)	7. Isolation and switching		8.6 Cable entry holes in ceiling above luminaires, sized or sealed so as to restrict the spread of fire:	(.....)
6.20 Band II cables segregated / separated from Band I cables:	(LIM.....)	7.1 Isolators		List number and location of luminaires inspected on a separate page:	Page No. (N/A.....)
6.21 Cables segregated / separated from non-electrical services:	(LIM.....)	a) Presence and condition of appropriate devices:	(.....)	8.7 Recessed luminaires (e.g. downlighters)	(N/A.....)
6.22 Termination of cables at enclosures (<i>indicate extent of sampling in PART 7 of report</i>)	(LIM.....)	b) Acceptable location (local / remote):	(.....)	a) Correct type of lamps fitted:	(N/A.....)
a) Connections under no undue strain:	(.....)	c) Capable of being secured in the OFF position:	(.....)	b) Installed to minimise build-up of heat	(N/A.....)
b) No basic insulation of a conductor, visible outside an enclosure:	(.....)	d) Correct operation verified:	(.....)	c) No signs of overheating to surrounding building fabric:	(N/A.....)
c) Connections of live conductors adequately enclosed:	(.....)	e) Clearly identified by position and / or durable markings:	(.....)	d) No signs of overheating to conductors / terminations:	(N/A.....)
d) Adequacy of connection at point of entry to enclosure:	(.....)	f) Warning label posted in situations where live parts cannot be isolated by the operation of a single device:	(N/A.....)		
6.23 Temperature rating of cable insulation adequate:	(.....)	7.2 Switching off for mechanical maintenance			
6.24 Condition of accessories including socket-outlets, switches and joint boxes satisfactory:	(.....)	a) Presence and condition of appropriate devices:	(.....)		
6.25 Suitability of accessories for external influences:	(.....)	b) Acceptable location:	(.....)		
		c) Capable of being secured in the OFF position:	(.....)		
		d) Correct operation verified:	(.....)		
		e) Clearly identified by position and / or durable marking(s):	(.....)		
		7.3 Emergency switching off / stopping			
		a) Presence and condition of appropriate devices:	(.....)		
		b) Readily accessible for operation where danger might occur:	(.....)		
		c) Correct operation verified:	(.....)		
		7.4 Functional switching			
		a) Presence and condition of appropriate devices:	(.....)		
		b) Correct operation (functionality) verified:	(.....)		

SCHEDULE OF ITEMS INSPECTED BY

Name (capital): BRIAN MCCARTHY
Signature:  Date: 27/07/2022

PART 11 : SCHEDULES AND ADDITIONAL PAGES

Schedule of Inspections	Schedule of Circuit Details and Test Results for the installation	Additional pages, including data sheets for additional sources	Special installations or locations (<i>indicated in item 9, above</i>)	Continuation sheets
Page No(s): (4 & 5.....)	Page No(s): (6, 7.....)	Page No(s): (8.....)	Page No(s): (None.....)	Page No(s): (None.....)

The pages identified are an essential part of this report (see Regulation 653.2).

All fields must be completed. Enter either, as appropriate: '✓' if Acceptable condition; 'N/A' if Not applicable; 'LIM' if a Limitation exists; or Code appropriately – CODE 'C1', 'C2', 'C3' or 'F1' (codes to be recorded in PART 6, with additional comments (where appropriate) on attached numbered sheets)

PART 12: SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing

CODES for Type of wiring		(A) Thermoplastic insulator/ sheathed cables	(B) Thermoplastic cables in metallic conduit	(C) Thermoplastic cables in non-metallic conduit		(D) Thermoplastic cables in metallic trunking			(E) Thermoplastic cables in non-metallic trunking	(F) Thermoplastic / SWA cables	(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(I) other - state N/A											
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671)	Protective device			RCD Operating current, $I_{\Delta n}$ (mA)	Maximum permitted Z_s for installed protective device* (Ω)	Circuit impedances (Ω)			Insulation resistance			Polarity	Max. measured earth fault loop impedance, Z_s (Ω)	RCD operating time (ms)	Test buttons				
					Live (mm ²)	CPC (mm ²)		BS (EN)	Type	Rating (A)			Short-circuit capacity (kA)	(Line) Z_l	(Neutral) Z_n	(CPC) Z_c	($R_1 + R_2$) (complete at least one column)	R_2				Live / Live (M Ω)	Live / Earth (M Ω)	Test voltage DC (V)	RCD (✓)	AFPD (✓)
1L1	Sockets: Kitchen	A	B	5	2x2.5	2x1.5	0.4	3871	2	32	6	N/A	0.98	0.43	0.43	0.69	0.09		200	200	500	✓	0.3		N/A	N/A
1L2	Sockets: Classrooms	A	B	6	2x2.5	2x1.5	0.4	3871	2	32	6	N/A	0.98	0.59	0.59	0.91	0.24		200	200	500	✓	0.45		N/A	N/A
1L3	Sockets: Offices/Drill Hall	A	B	4	2x2.5	2x1.5	0.4	3871	2	32	6	N/A	0.98	0.28	0.28	0.50	0.19		200	200	500	✓	0.4		N/A	N/A
2L1	Spare																									
2L2	Water Heaters: WC's	A	B	2	2x2.5	2x1.5	0.4	3871	2	32	6	N/A	0.98	0.5	0.5	0.81	0.2		200	200	500	✓	0.41		N/A	N/A
2L3	Spare																									
3L1	Lights: Drill Hall	A	B	4	1	1	0.4	3871	2	6	6	N/A	5.20				0.26		200	200	500	✓	0.45		N/A	N/A
3L2	Spare																									
3L3	Socket/Heater pt: Drill Hall	A	B	2	2.5	1.5	0.4	3871	2	20	6	N/A	1.56				0.15		200	200	500	✓	0.36		N/A	N/A
4L1	Heater points: Drill Hall/Class 1	A	B	2	2.5	1.5	0.4	3871	2	20	6	N/A	1.56				0.36		200	200	500	✓	0.58		N/A	N/A
4L2	Heater points: Class 1 & 2	A	B	2	2.5	1.5	0.4	3871	2	20	6	N/A	1.56				0.32		200	200	500	✓	0.43		N/A	N/A
4L3	Heater points: Class 2 & 3	A	B	2	2.5	1.5	0.4	3871	2	20	6	N/A	1.56				0.44		200	200	500	✓	0.63		N/A	N/A
5L1	Lights: Offices	A	B	4	1	1	0.4	3871	2	6	6	N/A	5.20				0.42		200	200	500	✓	0.53		N/A	N/A
5L2	Lights: Kitchen/WC's	A	B	5	1	1	0.4	3871	2	6	6	N/A	5.20				0.79		200	200	500	✓	1.15		N/A	N/A
5L3	Lights: Classrooms	A	B	5	1	1	0.4	3871	2	6	6	N/A	5.20				0.9		200	200	500	✓	0.97		N/A	N/A
6TP	Spare																									
7TP	Spare																									
8TP	Spare																									

DISTRIBUTION BOARD (DB) DETAILS
(to be completed in every case)

DB designation: DB1
Location of DB: Cupboard in Drill Hall

TESTED BY

Name (capital): BRIAN MCCARTHY
Signature: 

Position: Electrician
Date: 27/07/2022

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (N/A) Nominal voltage: (N/A) V No. of phases: (N/A)

Overcurrent protection device for the distribution circuit Type: (BS EN N/A) Rating: (N/A) A

Associated RCD (if any) Type: (BS EN N/A) No. of poles: (N/A) mA Operating time (N/A) ms

Characteristics at this DB Confirmation of supply polarity: (N/A) Phase sequence confirmed (where appropriate): (N/A) Z_s (N/A) Ω I_{pf} (N/A) kA

TEST INSTRUMENTS (enter serial number against each instrument used)

Multi-function: (101389357) Continuity: (N/A)

Insulation resistance: (N/A) Earth fault loop impedance: (N/A)

Earth electrode resistance: (N/A) RCD: (N/A)



Electrical and
Plumbing Contractors

CONTINUATION SHEET:

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

25689236

ISN18C

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing :

CODES for Type of wiring		(A) Thermoplastic insulated / d /	(B) Thermoplastic cables in sheathed cables	(C) Thermoplastic cables in non-metallic conduit	(D) Thermoplastic cables in metallic trunking	(E) Thermoplastic cables in non-metallic trunking	(F) Thermoplastic / SVIA cables	(G) Thermosetting / SVIA cables	(H) Mineral-insulated cables	(I) other - state: N/A															
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671)	Protective device			RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device*	Circuit impedances (Ω)			Insulation resistance			Polarity	Max. measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons			
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating (A)			Short-circuit capacity (kA)	(Line) r ₁	(Neutral) r _n	(cpc) r ₂	(R ₁ + R ₂) R ₂	Live / Live (MΩ)				Live / Earth (MΩ)	Test voltage DC (V)	RCD (✓)	AFDD (✓)
1	Sockets: Sim Room	A	B	3	2x2.5	2x1.5	0.4	61009	C	32	10	30	0.68	0.43	0.43	0.81	0.01	>999	>999	500	✓	0.4	28.7	✓	N/A
2	Cooker	A	B	1	6	2.5	0.4	61009	C	32	10	30	0.68				0.01	>999	>999	500	✓	0.25	28.8	✓	N/A
3	Heater: Drill Hall	A	B	1	2.5	1.5	0.4	61009	C	20	10	30	1.09				0.01	>999	>999	500	✓	0.52	28.7	✓	N/A
4	Socket: Store	A	B	1	2.5	1.5	0.4	61009	C	20	10	30	1.09				0.01	>999	>999	500	✓	0.37	28.9	✓	N/A
5	Emergency Lighting	A	B	6	1	1	0.4	61009	C	6	10	30	3.64				0.01	>999	>999	500	✓	0.57	28.7	✓	N/A
6	Lights: Outside	A	B	4	1	1	0.4	61009	C	6	10	30	3.64				0.01	>999	>999	500	✓	0.45	28.7	✓	N/A
7	Alarm/Heat Trace	A	B	2	2.5	1.5	0.4	61009	C	6	10	30	3.64				0.01	>999	>999	500	✓	0.43	28.6	✓	N/A
8	Contactor control circuit	A	B	1	1	1	0.4	60898	B	6	10	N/A	7.28				0.01	>999	>999	500	✓	0.34		N/A	N/A
9	Spare																								
10	Spare																								
11	Spare																								
12	Spare																								
13	Spare																								
14	Spare																								
									</																

DISTRIBUTION BOARD (DB) DETAILS	DB designation: DB2	TESTED BY	Name (capital): BRIAN MCCARTHY	Position: Electrician
(to be completed in every case)	Location of DB: Cupboard in Drill Hall	Signature:		Date: 27/07/2022

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (N/A)	Nominal voltage: (N/A) V	No. of phases: (N/A)
Overcurrent protection device for the distribution circuit	Type: (BS EN N/A)	Rating: (N/A) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Characteristics at this DB	Confirmation of supply polarity: (N/A)	Phase sequence confirmed (where appropriate): (N/A)
		Operating time (N/A) ms
		Earth fault loop impedance: (N/A) Ω
		Earth electrode resistance: (N/A) Ω
		RCD: (N/A)

TEST INSTRUMENTS (enter serial number against each instrument used)

Multi-function: 101389357	Continuity: (N/A)
Insulation resistance: (N/A)	Earth fault loop impedance: (N/A)
Earth electrode resistance: (N/A)	RCD: (N/A)

GENERAL CONTINUATION SHEET

NOTES

General Condition Of the Installation

There is a lack of RCD circuit protection. Three sockets in the drill hall have been replaced with RCD sockets, whilst these provide protection against faulty appliances the actual circuitry is not protected. There is no other RCD protection to any of the original installation emanating from DB1, lighting, heater points and sockets (except the three previously mentioned). DB2 which was installed at a later date, have circuits which are RCD protected.
Poor design of the emergency lighting system. These have been wired on a dedicated circuit. They should be connected to the lighting circuits specific to the areas they serve.

NOTES FOR RECIPIENT

THIS CONDITION REPORT IS AN IMPORTANT AND VALUABLE DOCUMENT WHICH SHOULD BE RETAINED FOR FUTURE USE

The purpose of periodic inspection is to determine, so far as is reasonably practicable, whether an electrical installation is in a satisfactory condition for continued service. This report provides an assessment of the condition of the electrical installation identified overleaf at the time it was inspected and tested, taking into account the stated extent of the installation and the limitations of the inspection and testing.

This report has been issued in accordance with the national standard for the safety of electrical installations, *BS 7671: 2018 – Requirements for Electrical Installations*.

The report identifies any damage, deterioration, defects and/or conditions found by the inspector which may give rise to danger (see PART 6), together with any items for which improvement is recommended. If you were the person ordering this report, but not the user of the installation, you should pass this report, or a full copy of it including these notes, the schedules and additional pages (if any), immediately to the user.

This report should be retained in a safe place and shown to any person inspecting or undertaking further work on the electrical installation in the future. If you later vacate the property, this report will provide the new user with an assessment of the condition of the electrical installation at the time the periodic inspection was carried out.

Where the installation incorporates a residual current device (RCD) there should be a notice at or near the device stating that it should be tested every six months. For safety reasons it is important that this instruction is followed.

For safety reasons, the electrical installation should be re-inspected at appropriate intervals by a skilled person or persons, competent in such work. NICEIC* recommends that you engage the services of an NICEIC Approved Contractor for the inspection.

The recommended date by which the next inspection should be carried out is stated in PART 5 of this report. There should also be a notice at or near the main switchboard or distribution board/consumer unit indicating when the next inspection of the installation is due.

Only an NICEIC Approved Contractor or Conforming Body is authorised to issue this NICEIC Electrical Installation Condition Report. You should have received the report marked 'Original' and the Approved Contractor should have retained the report marked 'Duplicate'.

This report form is intended to be issued only for the purpose of reporting on the condition of an existing electrical installation and must not be issued to certify new electrical installation work including the replacement of a distribution board or consumer unit.

The report consists of at least six numbered pages. Additional numbered pages may have been provided to permit further relevant information relating to the installation to be recorded. For installations having more than one distribution board or more circuits than can be recorded on PART 12, one or more additional *Schedules of Circuit Details and Test Results* should form part of the report. The report is invalid if any of the schedules identified in PART 10 are missing. The report has a printed serial number, which is traceable to the Contractor to which it was supplied.

PART 7 (Details and limitations) should identify fully the extent of the installation covered by this report and any limitations on the inspection and testing. The inspector should have agreed these aspects with the person ordering the report and with other interested parties (licensing authority, insurance company, mortgage provider and the like) before the inspection was carried out.

Operational limitations may have been encountered during the inspection such as inability to gain access to parts of the installation or to an item of equipment. The inspector should have noted any such limitations in PART 7. It should be noted that the greater the limitations applying to a report, the less its value from the safety aspect.

A declaration should have been given by the inspector in PART 4 of the report. The declaration must reflect the statement given in PART 3, which summarises the observations and recommendations made in PART 6. Where one or more observations have been made in PART 6, the Classification code given to each by the inspector indicates the degree of urgency with which remedial action needs to be taken to restore the installation to a safe working condition.

Where the inspector has indicated an observation as code C1 (danger present) **the safety of those using the installation is at risk**. Wherever practicable, items classified as (C1) should be made safe on discovery, and it is recommended that a skilled person(s) competent in electrical installation work undertakes the necessary remedial work immediately.

Where the inspector has indicated an observation as code C2 (potentially dangerous) **the safety of those using the installation may be at risk**, and it is recommended that a skilled person(s) competent in electrical installation work undertakes the necessary remedial work as a matter of urgency.

Where the inspector has indicated that an item requires further investigation (FI), the investigation should be carried out without delay to determine whether danger or potential danger exists. For further guidance on the Classification codes, please see the reverse of page 2.

Where the installation can be supplied by more than one source, such as the public supply and a standby generator or microgenerator, this should be identified in PART 8 *Supply Characteristics and Earthing Arrangements*, and the *Schedules of Circuit Details and Test Results* (PART 12) compiled accordingly.

Where inadequacies in the intake equipment have been observed (Item 1 of PART 10), the person ordering the inspection should inform the distributor and/or supplier as appropriate.

Should the person ordering this report have reason to believe that it does not reasonably reflect the condition of the electrical installation reported on, that person should in the first instance raise the specific concerns in writing with the Approved Contractor. If the concerns remain unresolved, the person ordering this report may make a formal complaint to NICEIC, for which purpose a complaint form is available on request.

The complaints procedure offered by NICEIC is subject to certain terms and conditions, full details of which are available upon application. NICEIC does not investigate complaints relating to the operational performance of electrical installations (such as lighting levels), or to contractual or commercial issues (such as time or cost).

** NICEIC is operated by Certsure LLP, a partnership between the Electrical Contractors' Association and the charity, Electrical Safety First. NICEIC maintains and publishes registers of electrical contractors that it has assessed against particular scheme requirements (including the technical standard of electrical work).*

For further information about electrical safety and how NICEIC
can help you, visit www.niceic.com

GUIDANCE FOR RECIPIENTS ON THE CLASSIFICATION CODES

Only one Classification code should be given for each recorded Observation

Classification code C1 (Danger present)

Where an observation has been given a Classification code C1, the safety of those using the installation is at risk and immediate remedial action is required.

The person responsible for the maintenance of the installation is advised to take action without delay to remedy the observed deficiency in the installation, or to take other appropriate action (such as switching off and isolating the affected parts) of the installation) to remove the danger. The NICEIC Approved Contractor issuing this report will be able to provide further advice.

NICEIC makes available 'Electrical Danger Notification' forms to enable inspectors to record, and then to communicate to the person ordering the report, any dangerous condition discovered.

Classification code C2 (Potentially dangerous)

Classification code C2 indicates that, whilst those using the installation may not be at immediate risk, urgent remedial action is required to remove potential danger. The NICEIC Approved Contractor issuing this report will be able to provide further advice.

It is important to note that the recommendation given at PART 5 of this report (Next Inspection) for the maximum interval until the next inspection is conditional upon all items which have been given a Classification code C1 and code C2 being remedied immediately and as a matter of urgency, respectively. It would not be reasonable for the inspector to indicate that the installation is in a satisfactory condition if any observation in this report has been given a code C1 or code C2 classification.

Classification code C3 (Improvement recommended)

Where an observation has been given a Classification code C3, the inspection and/or testing has revealed a non-compliance with the current safety standard which, whilst not presenting immediate or potential danger, would result in a significant safety improvement if remedied. Careful consideration should be given to the safety benefits of improving these aspects of the installation. The NICEIC Approved Contractor issuing this report will be able to provide further advice.

Code FI (Further investigation required without delay)

It should usually be possible for the inspector to attribute a Classification code to each observation without indicating a need for further investigation.

However, where 'FI' has been entered against an observation the inspector considers that further investigation of that observation is likely to reveal danger or potential danger that, due to the agreed extent or limitations of the inspection and/or testing, could not be fully identified at the time.

It would not be appropriate for the inspector to indicate that the installation is in a satisfactory condition if there is reasonable doubt as to whether danger or potential danger exists. Consequently, where the inspector has indicated 'Further investigation required without delay' (FI) the overall assessment of the installation (PART 3) should be marked as 'Unsatisfactory'.

If the inspector has indicated that an observation requires further investigation without delay, the person ordering this report is advised to arrange for the NICEIC Approved Contractor issuing the report (or another skilled person or persons competent in such work) to undertake further examination of that aspect of the installation as a matter of urgency, to determine whether or not danger or potential danger exists.

Further information

Further information on the application of Classification codes, primarily aimed at inspectors but of possible interest to persons ordering condition reports, can be found in Electrical Safety First's Best Practice Guide No 4 *Electrical Installation condition reporting: Classification Codes for domestic and similar electrical installations*. The guide can be viewed or downloaded free of charge from www.electricalsafetyfirst.org.uk

For further information about electrical safety and how NICEIC can help you, visit www.niceic.com