



**APPROVED
CONTRACTOR** Electrical and
Plumbing Contractors

This report is not valid if the serial
number has been defaced or altered

24273861

IPN18C

ELECTRICAL INSTALLATION CONDITION REPORT

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

PART 1 : DETAILS OF THE CONTRACTOR, CLIENT AND INSTALLATION

DETAILS OF THE CONTRACTOR

Registration No: 028288000 Branch No:
Trading Title: R J Electrical Services Ltd
Address: Unit 3a, Barnack Industrial Estate, Kingsway,
Salisbury
Postcode: SP2 0AW Tel No:

DETAILS OF THE CLIENT

Contractor Reference Number (CRN): 22092
Name: Wessex RFCA
Address: Wessex Reserve Forces & Cadets Association,
Mount House, Mount Street, TAUNTON, Somerset
Postcode: TA1 3QE Tel No: N/A

DETAILS OF THE INSTALLATION

Occupier: Royal Wessex Yeomanry HQ
Address: Royal Wessex Yeomanry HQ, Allenby Barracks
Bovington, WAREHAM, Dorset
Postcode: BH20 6JA Tel No: N/A

PART 2 : PURPOSE OF THE REPORT

Purpose for which this report is required: Scheduled inspection

Date(s) when inspection and testing was carried out: 04/10/2021 - 02/11/2021

Records available: (.....) ✓

Previous inspection report available: (.....) ✓

Previous report date: 03/01/2019

PART 3 : SUMMARY OF THE CONDITION OF THE INSTALLATION

General condition of the installation (in terms of electrical safety):

Good throughout, installed to a good standard. Some advisory see continuation page.

Estimated age of electrical installation: 21 (.....) years

Evidence of additions or alterations: (.....) ✓

Overall assessment of the installation is: **Satisfactory** (delete as appropriate)

PART 4 : DECLARATION

INSPECTION AND TESTING

I, being the person responsible for the inspection and testing of the electrical installation, particulars of which are described in PART 7, having exercised reasonable skill and care when carrying out the inspection and testing of the existing installation, hereby CERTIFY that the information in this report, including the observations (page 2) and the attached schedules, provides an accurate assessment of the condition of the electrical installation taking into account the stated extent of the installation and the limitations on the inspection and testing.

Name (capital): BRIAN MCCARTHY

Signature:

Date: 02/11/2021

Name (capital): ROBERT COOMBS

Signature:

Date: 03/11/2021

REVIEWED BY THE REGISTERED QUALIFIED SUPERVISOR FOR THE APPROVED CONTRACTOR

*An unsatisfactory assessment indicates that dangerous (CODE C1) and/or potentially dangerous (CODE C2) conditions have been identified in PART 6, or that Further Investigation (CODE FI) without delay is required.



APPROVED
CONTRACTOR
Electrical and
Plumbing Contractors

This report is not valid if the serial
number has been defaced or altered

24273861

IPN18C

ELECTRICAL INSTALLATION CONDITION REPORT

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

PART 7 : DETAILS AND LIMITATIONS OF THE INSPECTION AND TESTING

The inspection and testing has been carried out in accordance with BS 7671: 2018, as amended. Cables concealed within trunking and conduits, or cables and conduits concealed under floors, in inaccessible roof spaces and generally within the fabric of the building or underground, have not been visually inspected unless specifically agreed between the Client and the Inspector prior to inspection.

Details of the installation covered by this report: Fixed wiring only

Agreed limitations including the reasons, if any, on the inspection and testing: None

Agreed with (print name):

Extent of sampling: Approximately 10% of accessories were removed for visual inspection.

Operational limitations including the reasons: See continuation page.

By enquiry, measurement, or by calculation

PART 8 : SUPPLY CHARACTERISTICS AND EARTHING ARRANGEMENTS

System type and earthing arrangements

TN-C-S: (N/A) TN-S: (✓) TT: (N/A)

Other (state): N/A

Supply protective device

(BS EN) Non-verifiable

Type: (N/A) Rated current: (400) A

Number and type of live conductors

AC 1-phase, 2-wire: (N/A)

2-phase, 3-wire: (N/A)

3-phase, 3-wire: (N/A)

3-phase, 4-wire: (✓)

DC 2-wire: (N/A)

3-wire: (N/A)

Other: (N/A)

Nature of supply parameters

Nominal line voltage, $U_{(1)}$:

(400) V

Nominal line voltage to Earth, U_0 (1):

(230) V

Nominal frequency, f (1):

(50) Hz

Prospective fault current, I_{pf} (1)*:

(N/A) kA

External loop impedance, Z_e (1)*:

(N/A) Ω

PART 9 : PARTICULARS OF INSTALLATION REFERRED TO IN THIS REPORT

Means of Earthing

Distributor's facility: (✓)

Installation earth electrode: (N/A)

Where an earth electrode is used insert

Type – rod(s), tape, etc: None

Location: (N/A)

Electrode resistance to Earth: (N/A) Ω

Main protective conductors

Earthing conductor:

(material) Copper

Connection / continuity verified: (✓)

Main protective bonding conductors:

(material) Copper

Connection / continuity verified: (✓)

Main protective bonding connections

Water installation pipes: (✓)

Gas installation pipes: (✓)

Structural steel: (✓)

Oil installation pipes: (N/A)

Lightning protection: (N/A)

Other (state): N/A

Main switch / Switch-fuse / Circuit-breaker / RCD

Type: (BS EN) 60947-2

Location: (Plant Room)

No. of poles: (3)

Current rating: (1200) A

Rating / setting of device: (400) A

Voltage rating: (400) V

Where an RCD is used as the main switch

RCD rated residual operating current, $I_{\Delta n}$:

Measured operating time: (N/A) ms

Rated time delay: (N/A) ms

*Where the installation is supplied by more than one source, the higher or highest values of prospective fault current, I_{pf} , and external earth loop impedance, Z_e , must be recorded.

All fields must be completed. Enter either, as appropriate: '✓' if Acceptable condition; 'N/A' if Not applicable; 'LIM' if a Limitation exists;

or Code appropriately – CODE 'C1', 'C2', 'C3' or 'F' (codes to be recorded in PART 6, with additional comments (where appropriate) on attached numbered sheets)

This report is based on the model forms shown in Appendix 6 of BS 7671

Published by Certsure LLP Certsure LLP operates the NICEIC & ELECSA brands

Warwick House, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZX

@ Copyright Certsure LLP (July 2018)

ELECTRICAL INSTALLATION CONDITION REPORT

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

PART 10 : SCHEDULE OF ITEMS INSPECTED

1. External condition of electrical intake equipment (visual inspection only)
(If inadequacies are identified with the intake equipment, it is recommended the person ordering the report informs the appropriate authority.)

- | | | | |
|---------------------------|-------|-------------------------------|-------|
| 1.1 Service cable: | (N/A) | 1.2 Service head: | (N/A) |
| 1.3 Earthing arrangement: | (N/A) | 1.4 Meter tails: | (N/A) |
| 1.5 Metering equipment: | (N/A) | 1.6 Isolator (where present): | (N/A) |

2. Presence of adequate arrangements for parallel or switched alternative sources

- | | |
|---|-------|
| 2.1 Adequate arrangements where a generating set operates as a switched alternative to the public supply: | (N/A) |
| 2.2 Adequate arrangements where generating set operates in parallel with the public supply: | (N/A) |
| 2.3 Presence of alternative / additional supply arrangement warning notice(s) at or near equipment, where required: | (N/A) |

3. Automatic disconnection of supply

- | | |
|---|-------|
| 3.1 Main earthing and bonding arrangements | |
| a) Presence and condition of distributor's earthing arrangement: | (✓) |
| b) Presence and condition of earth electrode arrangement, if present: | (N/A) |
| c) Adequacy of earthing conductor size: | (✓) |
| d) Adequacy of earthing conductor connections: | (✓) |
| e) Accessibility of earthing conductor connections: | (✓) |
| f) Adequacy of main protective bonding conductor size(s): | (✓) |
| g) Adequacy of main protective bonding conductor connections: | (✓) |
| h) Accessibility of main protective bonding connections: | (✓) |
| i) Accessibility and condition of other protective bonding connections: | (✓) |
| j) Provision of earthing / bonding labels at all appropriate locations: | (✓) |

3.2 FELV

- | | |
|--|-----|
| a) Source providing at least simple separation: | (✓) |
| b) Plugs, socket-outlets and the like not interchangeable with those of other systems within the premises: | (✓) |

4. Other methods of protection

Details should be provided on separate sheets:

Page No. (.....)

5. Distribution equipment

- | | |
|---|-----|
| 5.1 Adequacy of working space / accessibility of equipment: | (✓) |
| 5.2 Security of fixing: | (✓) |
| 5.3 Condition of insulation of live parts: | (✓) |
| 5.4 Adequacy / security of barriers: | (✓) |
| 5.5 Condition of enclosure(s) in terms of IP rating: | (✓) |
| 5.6 Condition of enclosure(s) in terms of fire rating: | (✓) |
| 5.7 Enclosure not damaged / deteriorated so as to impair safety: | (✓) |
| 5.8 Presence and effectiveness of obstacles: | (✓) |
| 5.9 Presence of main switch(es), linked where required: | (✓) |
| 5.10 Operation of main switch(es) (functional check): | (✓) |
| 5.11 Correct identification of circuit protective devices: | (✓) |
| 5.12 Adequacy of protective devices for prospective fault current: | (✓) |
| 5.13 RCD(s) provided for fault protection – includes RCBOs: | (✓) |
| 5.14 RCD(s) provided for additional protection – includes RCBOs: | (✓) |
| 5.15 RCD(s) provided for protection against fire – includes RCBOs: | (✓) |
| 5.16 Manual operation of circuit-breakers and RCDs to prove disconnection: | (✓) |
| 5.17 Confirmation that integral test button/switch causes RCD(s) to trip when operated (functional check) | (✓) |
| 5.18 Presence of RCD six-monthly retest notice at or near equipment, where required: | (✓) |
| 5.19 Presence of diagrams, charts or schedules at or near equipment, where required: | (✓) |
| 5.20 Presence of non-standard (mixed) cable colour warning notices at or near equipment, where required: | (✓) |
| 5.21 Presence of next inspection recommendation label: | (✓) |
| 5.22 All other required labelling provided: | (✓) |
| 5.23 Compatibility of protective device(s), base(s) and other components: | (✓) |

5.24 Single-pole switching or protective devices in line conductors only: (✓)

5.25 Protection against mechanical damage where cables enter equipment: (✓)

5.26 Protection against electromagnetic effects where cables enter ferrromagnetic enclosures: (✓)

6. Distribution / final circuits

- | | |
|--|-------|
| 6.1 Identification of conductors: | (✓) |
| 6.2 Cables correctly supported throughout their length: | (✓) |
| 6.3 Condition of insulation of live parts: | (✓) |
| 6.4 Non-sheathed cables protected by enclosures in conduit, ducting or trunking: | (✓) |
| 6.5 Suitability of containment systems for continued use (including flexible conduit): | (✓) |
| 6.6 Cables correctly terminated in enclosures (indicate extent of sampling in PART 7 of report): | (✓) |
| 6.7 Indication of SPD(s) continued functionality confirmed: | (N/A) |
| 6.8 Adequacy of AFDD(s), where specified: | (N/A) |
| 6.9 Confirmation that conductor connections, including connections to busbars are correctly located in terminals and are tight and secure: | (✓) |
| 6.10 Examination of cables for signs of unacceptable thermal and mechanical damage / deterioration: | (✓) |
| 6.11 Adequacy of cables for current-carrying capacity with regard to the type and nature of installation: | (✓) |
| 6.12 Adequacy of protective devices; type and rated current for fault protection: | (✓) |
| 6.13 Presence and adequacy of circuit protective conductors: | (✓) |
| 6.14 Co-ordination between conductors and overload protective devices: | (✓) |
| 6.15 Cable installation methods / practices appropriate to the type and nature of installation and external influences: | (✓) |
| 6.16 Cables where exposed to direct sunlight, of a suitable type or adequately protected against solar radiation: | (✓) |
| 6.17 Cables adequately protected against damage and abrasion: | (✓) |

All fields must be completed. Enter either, as appropriate: '✓' if Acceptable condition; 'N/A' if Not applicable; 'LIM' if a Limitation exists; or Code appropriately – CODE 'C1', 'C2', 'C3' or 'F1' (codes to be recorded in PART 6, with additional comments (where appropriate) on attached numbered sheets)

ELECTRICAL INSTALLATION CONDITION REPORT

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

PART 10 : SCHEDULE OF ITEMS INSPECTED

- 6.18 Provision of additional protection by an RCD not exceeding 30 mA
- a) For all socket-outlets with a rated current not exceeding 32 A, unless exempt: (.....) (✓.....)
- b) Supplies for mobile equipment with a rated current not exceeding 32 A for use outdoors: (.....) (✓.....)
- c) For cables concealed in walls / partitions at a depth of less than 50 mm: (.....) (✓.....)
- d) For cables concealed in walls / partitions containing metal parts regardless of depth: (.....) (N/A.....)
- e) Circuits supplying luminaires within domestic (household) premises: (.....) (N/A.....)

Note: Older installations designed prior to BS 7671: 2018 may not have been provided with RCDs for additional protection.

- 6.19 Provision of fire barriers, sealing arrangements and protection against thermal effects: (.....) (LIM.....)
- 6.20 Band II cables segregated / separated from Band I cables: (.....) (✓.....)
- 6.21 Cables segregated / separated from non-electrical services: (.....) (✓.....)
- 6.22 Termination of cables at enclosures (Indicate extent of sampling in PART 7 of report)

- a) Connections under no undue strain: (.....) (✓.....)
- b) No basic insulation of a conductor, visible outside an enclosure: (.....) (✓.....)
- c) Connections of live conductors adequately enclosed: (.....) (✓.....)
- d) Adequacy of connection at point of entry to enclosure: (.....) (✓.....)

- 6.23 Temperature rating of cable insulation adequate: (.....) (✓.....)
- 6.24 Condition of accessories including socket-outlets, switches and joint boxes satisfactory: (.....) (C3.....)
- 6.25 Suitability of accessories for external influences: (.....) (✓.....)

- 6.26 Single-pole switching or protective devices in line conductors only: (.....) (✓.....)
- 6.27 Adequacy of connections, including CPCs, within accessories and to fixed and stationary equipment: (.....) (✓.....)

7. Isolation and switching

- 7.1 Isolators (.....) (✓.....)
- a) Presence and condition of appropriate devices: (.....) (✓.....)
- b) Acceptable location (local / remote): (.....) (✓.....)
- c) Capable of being secured in the OFF position: (.....) (✓.....)
- d) Correct operation verified: (.....) (✓.....)
- e) Clearly identified by position and / or durable markings: (.....) (✓.....)
- f) Warning label posted in situations where live parts cannot be isolated by the operation of a single device: (.....) (N/A.....)

- 7.2 Switching off for mechanical maintenance (.....) (✓.....)
- a) Presence and condition of appropriate devices: (.....) (✓.....)
- b) Acceptable location: (.....) (✓.....)
- c) Capable of being secured in the OFF position: (.....) (✓.....)
- d) Correct operation verified: (.....) (✓.....)
- e) Clearly identified by position and / or durable marking(s): (.....) (✓.....)

- 7.3 Emergency switching off / stopping (.....) (✓.....)
- a) Presence and condition of appropriate devices: (.....) (✓.....)
- b) Readily accessible for operation where danger might occur: (.....) (✓.....)
- c) Correct operation verified: (.....) (✓.....)

- 7.4 Functional switching (.....) (✓.....)
- a) Presence and condition of appropriate devices: (.....) (✓.....)
- b) Correct operation (functionality) verified: (.....) (✓.....)

8. Current-using equipment (permanently connected)
- 8.1 Condition of equipment in terms of IP rating: (.....) (✓.....)
- 8.2 Equipment does not constitute a fire hazard: (.....) (✓.....)
- 8.3 Enclosure not damaged / deteriorated so as to impair safety: (.....) (✓.....)
- 8.4 Suitability for the environment and external influences: (.....) (✓.....)
- 8.5 Security of fixing: (.....) (✓.....)
- 8.6 Cable entry holes in ceiling above luminaires, sized or sealed so as to restrict the spread of fire: (.....) (✓.....)

List number and location of luminaires inspected on a separate page: (.....) (N/A.....)

- 8.7 Recessed luminaires (e.g. downlighters) (.....) (N/A.....)
- a) Correct type of lamps fitted: (.....) (✓.....)
- b) Installed to minimise build-up of heat: (.....) (✓.....)
- c) No signs of overheating to surrounding building fabric: (.....) (✓.....)
- d) No signs of overheating to conductors / terminations: (.....) (✓.....)

9. List all special installations or locations covered by this report: (.....) (N/A.....)

Indicate if the relevant requirements of Part 7 are satisfied and append results of inspection on a separate numbered page. (.....) (.....)

SCHEDULE OF ITEMS INSPECTED BY

Name (capital): BRIAN MCCARTHY

Signature:  Date: 02/11/2021

PART 11 : SCHEDULES AND ADDITIONAL PAGES

Schedule of Inspections	Schedule of Circuit Details and Test Results for the installation	Additional pages, including data sheets for additional sources	Special installations or locations (indicated in item 9. above)	Continuation sheets
Page No(s): (.....) (4, 8, 5.....)	Page No(s): (.....) (6, 7-28.....)	Page No(s): (.....) (29-30.....)	Page No(s): (.....) (None.....)	Page No(s): (.....) (None.....)

The pages identified are an essential part of this report (see Regulation 653.2).

All fields must be completed. Enter either, as appropriate: '✓' if Acceptable condition; 'N/A' if Not applicable; 'LIM' if a Limitation exists; or Code appropriately – CODE 'C1', 'C2', 'C3' or 'FI' (codes to be recorded in PART 6, with additional comments (where appropriate) on attached numbered sheets)

This report is based on the model forms shown in Appendix 6 of BS 7671

Published by Certsure LLP Certsure LLP operates the NICEIC & ELECSA brands

Warwick House, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZX



ELECTRICAL INSTALLATION CONDITION REPORT

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

PART 12 : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing N/A

CODES for Type of wiring		Thermoplastic insulated / shielded cables		Thermoplastic cables in metallic conduit		Thermoplastic cables in non-metallic conduit		Thermoplastic cables in metallic trunking		Thermoplastic cables in non-metallic trunking		Thermoplastic / SWA cables		Thermosetting / SWA cables		Mineral-insulated cables		(O) other - state: N/A							
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served		Circuit conductor csa		Max. disconnection time (BS 7671) (s)		Protective device		RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max. measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons	
				(BS 7671)		Live (mm ²)	cpc (mm ²)	BS (EN)	Type	Rating	Short-circuit capacity (kA)			Ring final circuits only (measured end to end)	All circuits (complete at least one column)	Live / Live	Live / Earth	Test voltage DC (V)	RCD (✓)	AFDD (✓)					
1-TP	Supply to DB1	F	E	1	50	95	5	38-2	E	100	80	N/A	0.46	LIM	LIM	LIM	N/A	✓	0.31	✓	N/A	N/A			
2-TP	Supply to DB2	F	E	1	25	Arm	5	38-2	E	100	80	N/A	0.46	LIM	LIM	LIM	N/A	✓	0.29	✓	N/A	N/A			
3-TP	Supply to DB3	F	E	1	35	Arm	5	38-2	E	125	80	N/A	0.33	LIM	LIM	LIM	N/A	✓	0.38	✓	N/A	N/A			
4-TP	Supply to DB4	F	E	1	25	Arm	5	38-2	E	32	80	N/A	1.84	LIM	LIM	LIM	N/A	✓	0.32	✓	N/A	N/A			
5-TP	Supply to DB MP	F	E	1	25	Arm	5	38-2	E	40	80	N/A	1.35	LIM	LIM	LIM	N/A	✓	0.31	✓	N/A	N/A			
6-TP	Supply to DB6	F	E	1	25	Arm	5	38-2	E	40	80	N/A	1.35	LIM	LIM	LIM	N/A	✓	0.28	✓	N/A	N/A			
7-TP	Supply to DB7	F	E	1	25	16	5	38-2	E	63	80	N/A	0.82	LIM	LIM	LIM	N/A	✓	0.31	✓	N/A	N/A			
8-TP	Supply to DB8	F	E	1	25	16	5	38-2	E	63	80	N/A	0.82	LIM	LIM	LIM	N/A	✓	0.30	✓	N/A	N/A			
9-TP	Supply to DB9	F	E	1	25	Arm	5	38-2	E	100	80	N/A	0.46	LIM	LIM	LIM	N/A	✓	0.27	✓	N/A	N/A			
10-TP	Supply to DB10	F	E	1	25	Arm	5	38-2	E	100	80	N/A	0.46	LIM	LIM	LIM	N/A	✓	0.21	✓	N/A	N/A			
11-TP	Supply to DB11	F	E	1	70	Arm	5	38-2	E	100	80	N/A	0.46	LIM	LIM	LIM	N/A	✓	0.29	✓	N/A	N/A			
12-TP	Power Factor Correction	B	B	1	150	25	5	LIM	N/A					LIM	LIM	LIM	N/A		LIM		N/A	N/A			

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: MSB1 Plant Room	Location of DB:	TESTED BY Name (capital): BRIAN MCCARTHY Signature:	Position: Electrician Date: 04/10/2021
---	------------------------------------	-----------------------	--	---

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (N/A)	Nominal voltage: (N/A) V	No. of phases: (N/A)
Overcurrent protection device for the distribution circuit	Type: (BS EN N/A)	Rating: (N/A) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Characteristics at this DB	Confirmation of supply polarity: (N/A)	Phase sequence confirmed (where appropriate): (N/A) Z_s (N/A) Ω $I_{\Delta n}$ (N/A) kA
		Operating time (N/A) ms
		Insulation resistance: (N/A)
		Earth electrode resistance: (N/A)
		Continuity: (N/A)
		Earth fault loop impedance: (N/A)
		RCD: (N/A)



APPROVED
CONTRACTOR

Electrical and
Plumbing Contractors



This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET:

ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

Circuits/equipment vulnerable to damage when testing 12L1, 12L2, 12L3, 13L2, 14L3																					
Circuit description		Type of wiring		Thermoplastic insulated / sheathed cables		Thermoplastic cables in metallic conduit		Thermoplastic cables in non-metallic conduit		Thermoplastic cables in non-metallic trunking		Thermoplastic / SWA cables		Mineral-insulated cables		(O) other - stat.					
Circuit number	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device			RCD Operating current, $I_{\Delta n}$ (mA)	Maximum permitted Z_s for installed protective device* (Ω)	Circuit impedances (Ω)			Insulation resistance			RCD operating time (ms)	Test buttons		
				Live (mm ²)	cpc (mm ²)		Type	Rating (A)	Short-circuit capacity (kA)			Ring final circuits only (measured end to end)	All circuits (complete at least one column)	Live / Live (MΩ)	Live / Earth (MΩ)	Test voltage DC (V)					
												(Line) r_1	(Neutral) r_n	(cpc) r_2	$(R_1 + R_2)$	R_2	Polarity	Max measured earth fault loop impedance, Z_s (Ω)			
1-TP Exhaust Extract	B	B	1	4	2.5	0.4	60898	C	20	6	N/A	1.09				0.07		✓	0.35		
2L1 Spare																					
2L2 WC Extractor Fan	B	B	1	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.18		✓	0.47		
2L3 Spare																					
3-TP Spare																					
4L1 Spare																					
4L2 Water Heater: WC	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.12		✓	0.44		
4L3 Spare																					
5L1 Spare																					
5L2 Water Heater: WC	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.12		✓	0.41		
5L3 Spare																					
6L1 Socket: Paint Store	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.19		✓	0.28		
6L2 110V Transformer	B	B	1	6	2.5	0.4	60898	C	20	6	N/A	1.09				0.09		✓	0.23		
6L3 Socket: Tyre Store	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.45		✓	0.73		
7-TP Compressor	B	B	1	6	2.5	0.4	60898	C	32	6	N/A	0.68				0.2		✓	0.55		
8-TP Workshop Ramp	B	B	1	6	2.5	0.4	60898	C	32	6	N/A	0.68				0.07		✓	0.28		
9L1 Spare																					
9L2 Hand Dryer: WC	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.09		✓	0.25		

DISTRIBUTION BOARD (DB) DETAILS

DB designation: DB1

Location of DB: Garage Workshop

TESTED BY

Name (capital): BRIAN MCCARTHY

Signature:

Position: Electrician

Date: 27/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 1-TP) Nominal voltage: (400) V No. of phases: (3)

Overcurrent protection device for the distribution circuit Type: (BS EN 88-2) Rating: (100) A

Associated RCD (if any) Type: (BS EN N/A) No. of poles: (N/A) $I_{\Delta n}$ (N/A) mA Operating time (N/A) ms

Characteristics at this DB Confirmation of supply polarity: (✓) Phase sequence confirmed (where appropriate): (✓) Z_s (0.31) Ω I_{pr} (0.79) kA

TEST INSTRUMENTS (enter serial number against each instrument used)

Multi-function: (8189065) Continuity: (N/A)

Insulation resistance: (N/A) Earth fault loop impedance: (N/A)

Earth electrode resistance: (N/A) RCD: (N/A)

This form is based on the model forms shown in Appendix 6 of BS 7671

Published by Certsure LLP Certsure LLP operates the NICEIC & ELECSA brands

Warwick House, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZX

* Where figure is not taken from BS 7671, state source: (N/A)

Page 7 of 30

Original (to the person ordering the work)

CONTINUATION SHEET:
ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS
Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS
(Delete as appropriate)

Circuits/equipment vulnerable to damage when testing 12L1, 12L2, 12L3, 13L2, 14L3

CODES for Type of wiring										(A) Thermoplastic insulated/ sheathed cables										(B) Thermoplastic cables in metallic conduit		(C) Thermoplastic cables in non-metallic conduit		(D) Thermoplastic cables in metallic trunking		(E) Thermoplastic cables in non-metallic trunking		(F) Thermoplastic / SWA cables		(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(O) other - state:		N/A	
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max disconnection time (BS 7671) (s)	Protective device				RCD current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max. measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons													
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating	Short-circuit capacity (kA)			Operating current (kA)	Ring final circuits only (measured end to end)	All circuits (complete at least one column)	Live / Live (MΩ)	Live / Earth (MΩ)	Test voltage DC (V)																		
9L3	Sockets: Office	B	B	3	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.15	0.16	0.16	0.08	200	500	✓	0.26			RCD (✓)	AFDD (✓)												
10L1	Socket: Corridor	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.02	200	500	✓	0.24			N/A	N/A												
10L2	Hand Dryer: WC	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.09	200	500	✓	0.27			N/A	N/A												
10L3	Sockets: MTO	B	B	3	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.21	0.21	0.22	0.07	200	500	✓	0.36			N/A	N/A												
11-TP	Spare																																				
12L1	Lights: Service Bay	B	B	8	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.23	200	250	✓	0.45			N/A	N/A												
12L2	Lights: Garage	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.76	200	250	✓	1.66			N/A	N/A												
12L3	Lights: Tyre Store	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.56	200	250	✓	1.18			N/A	N/A												
13L1	Spare																																				
13L2	Lights: Garage	B	B	5	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.75	200	250	✓	1.66			N/A	N/A												
13L3	Spare																																				
14L1	Spare																																				
14L2	Lights: WC's	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.23	200	500	✓	0.65			N/A	N/A												
14L3	Lights: Office	B	B	9	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.27	200	250	✓	0.72			N/A	N/A												
15TP	Spare																																				
16L1	Spare																																				
16L2	Fan Heater: Service Bay	B	B	1	2.5	1.5	0.4	60898	B	16	10	N/A	2.73				0.31	200	500	✓	0.65			N/A	N/A												
16L3	Fan Heater: Service Bay	B	B	1	2.5	1.5	0.4	60898	B	16	10	N/A	2.73				0.07	200	500	✓	0.40			N/A	N/A												

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: DB1	TESTED BY	Name (capital): BRIAN MCCARTHY	Position: Electrician
	Location of DB: Garage Workshop	Signature:		Date: 27/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 1-TP)	Nominal voltage: (400) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (100) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (✓) Z_s (0.31) Ω	Operating time (N/A) ms
Characteristics at this DB	Confirmation of supply polarity: (✓)	Earth electrode resistance: (N/A) Ω

CONTINUATION SHEET:

ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing 1L1, 1L2, 1L3, 2L1, 2L2, 2L3, 3L1, 3L2, 3L3, 4L2, 4L3, 5L2, 5L3, 6L3

Circuit description																							Test buttons						
Circuit number	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device			RCD Operating current, I _{an} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max. measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons							
				Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating			Short-circuit capacity (kA)	Ring final circuits only (measured end to end)	All circuits (complete at least one column)	Live / Live (MΩ)	Live / Earth (MΩ)	Test voltage DC (V)	RCD				AFDD							
(A) Thermoplastic insulated / sheathed cables	(B) Thermoplastic cables in metallic conduit	(C) Thermoplastic cables in non-metallic conduit	(D) Thermoplastic cables in metallic trunking	(E) Thermoplastic cables in non-metallic trunking	(F) Thermoplastic / SWA cables	(G) Thermosetting / SWA cables	(H) Mineral-insulated cables	(I) other - state:															N/A						
L1	Lights: Servery	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				(R ₁ + R ₂)	R ₂	(MΩ)	(MΩ)	250	250	✓	0.52	✓	✓	N/A	N/A	
L2	Lights: Officers Mess	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.31			200	250	250	250	✓	0.62	✓	N/A	N/A	
L3	Lights: Mess	B	B	7	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.32			200	250	250	250	✓	0.65	✓	N/A	N/A	
L1	Lights: Servery	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.26			200	250	250	250	✓	0.58	✓	N/A	N/A	
L2	Lights: Officers Mess	B	B	9	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.35			200	250	250	250	✓	0.63	✓	N/A	N/A	
L3	Lights: Mess	B	B	7	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.33			200	250	250	250	✓	0.66	✓	N/A	N/A	
L1	Lights: Corridor	B	B	12	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.51			200	250	250	250	✓	0.82	✓	N/A	N/A	
L2	Lights: Kitchen	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.18			200	250	250	250	✓	0.46	✓	N/A	N/A	
L3	Lights: Mess	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.38			200	250	250	250	✓	0.69	✓	N/A	N/A	
L1	Spare																												
L2	Lights: Kitchen	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.21			200	250	250	250	✓	0.55	✓	N/A	N/A	
L3	Lights: Bar	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.24			200	250	250	250	✓	0.54	✓	N/A	N/A	
L1	Spare																												
L2	Lights: D30	B	B	2	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.31			200	250	250	250	✓	0.63	✓	N/A	N/A	
L3	Lights: Bar	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.29			200	250	250	250	✓	0.64	✓	N/A	N/A	
L1	Spare																												
L2	Spare																												
L3	Lights: D29 Store	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.33				200	250	250	250	✓	0.65	✓	N/A	N/A

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: DB2	TESTED BY	Name (capital): BRIAN MCCARTHY	Position: Electrician
	Location of DB: Plant Room	Signature:		Date: 04/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 2-TP)	Nominal voltage: (400) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (100) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (N/A)	Operating time (N/A) ms
Characteristics at this DB	Insulation resistance: (N/A)	Earth fault loop impedance: (N/A)
	Earth electrode resistance: (N/A)	RCD: (N/A)

CONTINUATION SHEET:

ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing 1L1,1L2,1L3,2L1,2L2,2L3,3L1,3L2,3L3,4L2,4L3,5L2,5L3,6L3

[illegible]

DISTRIBUTION BOARD (DB) DETAILS		TESTED BY	
DB designation:	DB2	Name (capital):	BRIAN MCCARTHY
Location of DB:	Plant Room	Signature:	
(to be completed in every case)		Position:	Electrician
		Date:	04/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 2-TP)

Nominal voltage: (400) V

No. of phases: (3)

Overcurrent protection device for the distribution circuit

Type: (BS EN 88-2) Rating: (.....) A

Associated RCD (if any)	Type: (BS EN)	No. of poles: ()	$I_{\Delta n}$ () mA	Operating time () ms
	N/A	N/A	N/A	N/A

Characteristics at this DB: ☒ Confirmation of supply polarity: (.....) Z_s 0.29 Ω I_n 1.7 kA

Enter a ☒ or value in the respective fields, as appropriate

* Where figure is not taken from BS 7671, state source: () N/A

Enter a (✓) or value in the respective fields, as appropriate.

@ Copyright Certsure LLP (July 2018)

Published by Certsure LLP
 Certsure LLP operates the NICEIC & E
 Warwick House, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZX

Warwick House, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZX

N/A

Page

30 of

30



APPROVED
CONTRACTOR

Electrical and
Plumbing Contractors



This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET: ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS										Circuits/equipment vulnerable to damage when testing N/A													
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device				RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)			Insulation resistance		Polarity	Max. measured earth fault loop impedance Z _s (Ω)	RCD operating time (ms)	Test buttons	
					Live (mm ²)	cpc (mm ²)		Type	Rating	Short-circuit capacity	(Line) r _l			(Neutral) r _n	(cpc) r _c	All circuits (complete at least one column)	Live / Live (MΩ)	Live / Earth (MΩ)				Test voltage DC (V)	RCD (✓)
1L1	32A Socket: Servery	B	B	1	6	2.5	0.4	60898	C	40	6	N/A	0.55	0.27	200	500	✓	✓	N/A	N/A	✓	✓	
1L2	Sockets: Officers Mess	B	B	4	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.41	0.44	0.14	0.05	200	500	✓	✓	N/A	✓
1L3	Sockets: Mess	B	B	4	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.55	0.58	0.16	0.11	200	500	✓	✓	N/A	✓
2L1	32A Socket: Servery	B	B	1	6	2.5	0.4	60898	C	40	6	N/A	0.55	0.38	200	500	✓	✓	N/A	N/A	✓	✓	
2L2	Kitchen: Fridge	B	B	1	4	2.5	0.4	60898	C	20	6	N/A	1.09	0.00	200	500	✓	✓	N/A	N/A	✓	✓	
2L3	Sockets: Kitchen Store (No Access)	B	B	3	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.33	0.35	0.09	LIM	200	500	✓	✓	N/A	✓
3L1	Sockets: Servery (No Access)	B	B	6	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.22	0.24	0.00	LIM	200	500	✓	✓	N/A	✓
3L2	Kitchen: Fridge	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09	0.00	200	500	✓	✓	N/A	N/A	✓	✓	
3L3	Store: Fridge (No Access)	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09	0.16	200	500	✓	✓	N/A	N/A	✓	✓	
4L1	Hand Dryer: WC	B	B	1	2.5	2.5	0.4	60898	C	32	6	30	0.68	0.15	0.16	0.00	0.00	200	500	✓	✓	N/A	✓
4L2	Sockets: Kitchen	B	B	6	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.18	0.22	0.12	LIM	200	500	✓	✓	N/A	✓
4L3	Sockets: bar (No Access)	B	B	4	2.5	2.5	0.4	61009	C	32	6	N/A	0.55	0.32	0.31	0.17	LIM	200	500	✓	✓	N/A	✓
5TP	Kitchen Extractor Hood	B	B	1	10	4	0.4	60898	C	40	6	N/A	0.55	0.02	200	500	✓	✓	N/A	N/A	✓	✓	
6L1	Socket: Cleaners (No Access)	B	B	3	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.12	0.12	0.12	LIM	200	500	✓	✓	N/A	✓
6L2	Dish Washer	B	B	1	4	4	0.4	60898	C	20	6	N/A	1.09	0.12	0.12	0.12	LIM	200	500	✓	✓	N/A	✓
6L3	Sockets: Bar (No Access)	B	B	3	2.5	2.5	0.4	60898	C	20	6	N/A	1.09	0.12	0.12	0.12	LIM	200	500	✓	✓	N/A	✓
7L1	Spare																						
7L2	Spare																						

DISTRIBUTION BOARD (DB) DETAILS

DB designation: DB3

(to be completed in every case)

TESTED BY

Name (capital): BRIAN MCCARTHY

Signature:

Position: Electrician

Date: 26/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 3-TP) Nominal voltage: 400 V No. of phases: 3

Overcurrent protection device for the distribution circuit Type: (BS EN 88-2) Rating: 125 A

Associated RCD (if any) Type: (BS EN N/A) No. of poles: (N/A) I_{Δn} (N/A) mA Operating time (N/A) ms

Characteristics at this DB Confirmation of supply polarity: (✓) Phase sequence confirmed (where appropriate): (N/A) Z_s (0.38) Ω I_{pr} (0.86) kA

TEST INSTRUMENTS (enter serial number against each instrument used)

Multi-function: 8189065 Continuity: N/A

Insulation resistance: N/A Earth fault loop impedance: N/A

Earth electrode resistance: N/A RCD: N/A

This form is based on the model forms shown in Appendix 6 of BS 7671

Published by Certsure LLP Certsure LLP operates the NICEIC & ELECSA brands

Warwick House, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZX

* Where figure is not taken from BS 7671, state source: (N/A)

Page 12 of 30



APPROVED
CONTRACTOR

Electrical and
Plumbing Contractors

This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET:

ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing N/A

CODES for Type of wiring			(A) Thermoplastic insulated / sheathed cables		(B) Thermoplastic cables in metallic conduit		(C) Thermoplastic cables in non-metallic conduit		(D) Thermoplastic cables in metallic trunking		(E) Thermoplastic cables in non-metallic trunking		(F) Thermoplastic / SWA cables		(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(I) other - state:		N/A																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa			Max. disconnection time (BS 7671) (s)	Protective device				RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Max measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																													
					Live (mm ²)	cpc (mm ²)	BS (EN)		Type	Rating (A)	Short-circuit capacity (kA)	Ring final circuits only (measured end to end)			All circuits (complete at least one column)		Live / Live (MΩ)	Live / Earth (MΩ)	Test voltage DC (V)	Polarity																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																	
												(Line) r ₁			(Neutral) r _n	(cpc) r ₂					(R ₁ + R ₂)			R ₂																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																													
7L3	Not Located	B	B		2.5	1.5	0.4	60898	C	20	6	N/A	1.09																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																								</

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: DB3	Name (capital): BRIAN MCCARTHY	Position: Electrician
	Location of DB: Store D27	Signature:	Date: 26/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 3-TP)	Nominal voltage: (400 V)	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (125 A)
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (N/A)	Z_s : (0.38 Ω)
Operating time (N/A) ms	$I_{\Delta n}$: (N/A) mA	I_{pr} : (0.86) kA

TEST INSTRUMENTS (enter serial number against each instrument used)		
Multi-function: (8189065)	Continuity: (N/A)	
Insulation resistance: (N/A)	Earth fault loop impedance: (N/A)	
Earth electrode resistance: (N/A)	RCD: (N/A)	

This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISBN18C

CONTINUATION SHEET:
ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS
Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing N/A

[illegible]

DISTRIBUTION BOARD (DB) DETAILS

(to be completed in every case)

TESTED BY

Name (capitals): **BRIAN MCCARTHY**

Signature:

Position: Electrician

Date: 07/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: / MSB1 - 5-TP

Supply to DB is from:	Nominal voltage: (.....) V	No. of phases: (.....)
-----------------------	----------------------------	------------------------

Overcurrent protection device for the distribution circuit

Type: (BS EN 88-2) Rating: (40) A

Associated RCD (if any)	Type: (BSEN)	No. of poles: (3)	$I_{\Delta n}$ (.....) mA	Operating time (.....) ms
	Type: (BSEN)	No. of poles: (3)	$I_{\Delta n}$ (.....) mA	Operating time (.....) ms

Characteristics at this DB	Confirmation of supply polarity (✓)	Phase sequence confirmed (where appropriate) / N/A	10	1.1	11A
Characteristics at this DB	✓	Phase sequence confirmed (where appropriate) / N/A	10	1.1	11A

This form is based on the model forms shown in Appendix 6 of BS 7671

Published by Certsure LLP Certsure LLP operates the NICEIC & ELECSA brands

warwick house, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZAX

Enter a (✓) or value in the respective fields, as appropriate.

@ Copyright Certsure LLP (July 2018)

N/A
state source. (

.....\source\

State source: (	N/A
-----------------	-----

.....

150

Page 16 of 30

1141

This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET:
ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS
Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS
(Delete as appropriate)

Circuits/equipment vulnerable to damage when testing: 1L1 1L2 1L3 2L1 2L2 3L2 3L3 4L2 4L3 5L1 5L2

CODES for Type of wiring			(A) Thermoplastic insulated / sheathed cables		(B) Thermoplastic cables in metallic conduit	(C) Thermoplastic cables in metallic conduit		(D) Thermoplastic cables in metallic trunking		(E) Thermoplastic cables in non-metallic trunking		(F) Thermoplastic / SWA cables	(G) Thermosetting / SWA cables	(H) Mineral-insulated cables	(I) Other - state:		N/A							
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device			RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)			Insulation resistance		Polarity	Max measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons			
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating			Short-circuit capacity (kA)	Ring final circuits only (measured end to end)	All circuits (complete at least one column)	Live / Live (MΩ)	Live / Earth (MΩ)				Test voltage DC (V)	RCD (✓)	AFDD (✓)	
1L1	Lights: RHQ Store +	B	B	8	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.27		200	250	✓	0.59		N/A	N/A
1L2	Lights: HQN Stores	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.23		200	250	✓	0.53		N/A	N/A
1L3	Lights: Main Entrance	B	B	2	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.21		200	250	✓	0.55		N/A	N/A
1L1	Lights: Corridor 4	B	B	7	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.31		200	250	✓	0.65		N/A	N/A
1L2	Lights: Plant Room	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.19		200	250	✓	0.54		N/A	N/A
1L3	Spare																							
1L1	Lights: Quad Column	F	D	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09			0.64		200	500	✓	0.97		N/A	N/A
1L2	Lights: Training Rm	B	B	10	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.39		200	250	✓	0.76		N/A	N/A
1L3	Lights: Mess Rm	B	B	8	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.38		200	250	✓	0.72		N/A	N/A
1L1	Lights: Quad Column	F	D	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09			0.63		200	500	✓	0.99		N/A	N/A
1L2	Lights: Kitchen corridor	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	1.09			0.44		200	250	✓	0.74		N/A	N/A
1L3	Lights: Corridor 6	B	B	10	2.5	2.5	0.4	60898	C	10	6	N/A	1.09			0.36		200	250	✓	0.72		N/A	N/A
1L1	Contactors Control	B	B	1	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.02		200	250	✓	0.09		N/A	N/A
1L2	Lights: Officers Mess	B	B	8	2.5	2.5	0.4	60898	C	10	6	N/A	2.19			0.44		200	250	✓	0.72		N/A	N/A
1L3	Spare																							
1TP	Spare																							
1TP	Spare																							
1TP	Spare																							

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: DB6	Location of DB: Plant Room	TESTED BY Name (capital): BRIAN MCCARTHY Signature:	Position: Electrician Date: 05/10/2021
---	---------------------	----------------------------	--	---

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 6-TP)	Nominal voltage: (400) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (40) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (N/A)	Z_s (Ω) 0.28
Operating time (N/A) ms	$I_{\Delta n}$ (mA) N/A	I_{pf} (1.1) kA
Characteristics at this DB	Earth electrode resistance: (N/A)	RCD: (N/A)
Multi-function: (8189065)	Continuity: (N/A)	Earth fault loop impedance: (N/A)
Insulation resistance: (N/A)	Earth fault loop impedance: (N/A)	RCD: (N/A)
Earth electrode resistance: (N/A)	RCD: (N/A)	Earth fault loop impedance: (N/A)



APPROVED
CONTRACTOR

Electrical and
Plumbing Contractors



This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET:

ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing: N/A

CODES for Type of wiring										(A) Thermoplastic insulated / sheathed cables		(B) Thermoplastic cables in metallic conduit		(C) Thermoplastic cables in non-metallic conduit		(D) Thermoplastic cables in metallic trunking		(E) Thermoplastic cables in non-metallic trunking		(F) Thermoplastic / SWA cables		(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(I) other - state: N/A			
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device			RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons						
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating			Short-circuit capacity (kA)	Ring final circuits only (measured end to end)		All circuits (complete at least one column)		Live / Live (MΩ)	Live / Earth (MΩ)				Test voltage DC (V)						
														(Line) r ₁	(Neutral) r _n	(cpc) r ₂	(R ₁ + R ₂)							R ₂					
1L1	Spare																												
1L2	Sockets: Classroom 2	B	B	6	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.33	0.33	0.01	0.02		200	500		✓	0.27	19		✓		N/A	
1L3	Spare																												
2TP	Spare																												
3L1	Spare																												
3L2	Spare																												
3L3	Supply to Patch Panel	A	100	1	2.5	1.5	0.4	60898	B	16	10	N/A	2.73				0.21		200	500	✓	0.59			N/A		N/A		
4TP	Spare																												
5TP	Spare																												
6TP	Spare																												
																</													

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: DB7 Location of DB: Classroom 2	TESTED BY Name (capital): BRIAN MCCARTHY Signature:	Position: Electrician Date: 11/10/2021
---	--	--	---

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 7-TP)	Nominal voltage: (400) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (63) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (3)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (✓)	$I_{\Delta n}$ (N/A) mA
Operating time (N/A) ms	Z_s (0.31) Ω	I_{pr} (0.82) kA

TEST INSTRUMENTS (enter serial number against each instrument used)

Multi-function: (8189065)	Continuity: (N/A)
Insulation resistance: (N/A)	Earth fault loop impedance: (N/A)
Earth electrode resistance: (N/A)	RCD: (N/A)

CONTINUATION SHEET:
ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS
Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS
(Delete as appropriate)

Circuits/equipment vulnerable to damage when testing N/A

CODES for Type of wiring			Thermoplastic insulated / sheathed cables		Thermoplastic cables in metallic conduit		Thermoplastic cables in non-metallic conduit		Thermoplastic cables in non-metallic trunking		Thermoplastic cables in metallic trunking		Thermoplastic cables in non-metallic trunking		Thermoplastic / SWA cables		Thermosetting / SWA cables		Mineral-insulated cables		(Q) other - state:		N/A		
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device				RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max. measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons	
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating (A)	Short-circuit capacity (kA)			Ring final circuits only (measured end to end)		All circuits (complete at least one column)	Live / Live	Live / Earth	Test voltage DC (V)						
														(Line) r ₁	(Neutral) r _n					(cpc) r ₂				(R ₁ + R ₂) R ₂	
1L1	Sockets: Classroom 1	B	B	6	2.5	2.5	0.4																		
1L2	Spare																								
1L3	Spare																								
2TP	Spare																								
3TP	Spare																								
4TP	Spare																								
5TP	Spare																								
6TP	Spare																								

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: DB8	TESTED BY	Name (capital): BRIAN MCCARTHY	Position: Electrician
	Location of DB: Classroom 1	Signature: 		Date: 11/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 8-TP)	Nominal voltage: (400) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (63) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (3)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (✓) Z _s (0.84) Ω	Operating time (N/A) ms
Characteristics at this DB	Earth electrode resistance: (N/A)	Earth fault loop impedance: (N/A)
	Insulation resistance: (N/A)	Continuity: (N/A)

Page 21 of 30

This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET:
ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS
Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing 1L1, 1L2, 1L3, 2L1, 2L2, 2L3, 3L1, 3L2, 3L3, 4L1, 4L2, 4L3, 5L1, 5L2, 5L3, 6L1, 6L2, 6L3, 7L1, 7L2, 7L3, 8L1, 8L2, 8L3, 9L1, 9L2, 9L3

CODES for Type of wiring			(A) Thermoplastic insulated / sheathed cables		(B) Thermoplastic cables in metallic conduit		(C) Thermoplastic cables in non-metallic conduit		(D) Thermoplastic cables in metallic trunking		(E) Thermoplastic cables in non-metallic trunking		(F) Thermoplastic / SWA cables		(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(I) other - state:		N/A				
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device		RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons			
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type			Rating	Short-circuit capacity (kA)	(Line) r ₁	(Neutral) r _n	(cpc) r ₂	All circuits (complete at least one column)	Live / Live (MΩ)				Live / Earth (MΩ)	Test voltage DC (V)	RCD (✓)	AFDD (✓)
7L1	Lights: D03/04	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.26		200	250	250	✓	0.63	N/A	N/A
7L2	Lights: D05/06	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.19		200	250	250	✓	0.56	N/A	N/A
7L3	Lights: D15/16	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.18		200	250	250	✓	0.55	N/A	N/A
8L1	Spare																								
8L2	Lights: D52/53	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.23		200	250	250	✓	0.54	N/A	N/A
8L3	Lights: D45/46	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.22		200	250	250	✓	0.54	N/A	N/A
9L1	Lights: Corridor/D14	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.28		200	250	250	✓	0.59	N/A	N/A
9L2	Lights: D40/41/44	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.24		200	250	250	✓	0.62	N/A	N/A
9L3	Lights: Drying room	B	B	2	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.25		200	250	250	✓	0.58	N/A	N/A
10L1	Lights: Corridor	B	B	2	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.18		200	250	250	✓	0.56	N/A	N/A
10L2	Lights: Male WC	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.22		200	250	250	✓	0.58	N/A	N/A
10L3	Lights: Female WC	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.24		200	250	250	✓	0.57	N/A	N/A
11L1	Lights: Corridor	B	B	2	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.16		200	250	250	✓	0.54	N/A	N/A
11L2	Lights: Gym	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.22		200	250	250	✓	0.59	N/A	N/A
11L3	Spare																								
12L1	Spare																								
12L2	Lights: Training Rm	B	B	4	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.27		200	250	250	✓	0.63	N/A	N/A
12L3	Lights: Male Locker	B	B	9	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.29		200	250	250	✓	0.68	N/A	N/A

DISTRIBUTION BOARD (DB) DETAILS	DB designation: DB9	TESTED BY	Name (capital): BRIAN MCCARTHY	Position: Electrician
(to be completed in every case)	Location of DB: Plant Room	Signature:		Date: 07/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 9-TP) Nominal voltage: (400) V No. of phases: (3))

Overcurrent protection device for the distribution circuit Type: (BS EN 88-2) Rating: (100) A)

Associated RCD (if any) Type: (BS EN N/A) No. of poles: (N/A))

Characteristics at this DB Confirmation of supply polarity: (✓)) Phase sequence confirmed (where appropriate): (✓) Z_s (0.29) Ω I_{pf} (0.84) kA)

TEST INSTRUMENTS (enter serial number against each instrument used)

Multi-function: (8189065) Continuity: (N/A))

Insulation resistance: (N/A)) Earth fault loop impedance: (N/A))

Earth electrode resistance: (N/A)) RCD: (N/A))



APPROVED
CONTRACTOR

Electrical and
Plumbing Contractors

This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET:

ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 - Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing 1L1, 1L2, 1L3, 2L1, 2L2, 2L3, 3L1, 3L2, 3L3, 4L1, 4L2, 4L3, 5L1, 5L2, 5L3, 6L1, 6L2, 6L3, 7L1, 7L2, 7L3, 8L1, 8L2, 8L3, 9L1, 9L2,

CODES for Type of wiring																													
(A) Thermoplastic insulated / sheathed cables					(B) Thermoplastic cables in metallic conduit			(C) Thermoplastic cables in non-metallic conduit			(D) Thermoplastic cables in metallic trunking				(E) Thermoplastic cables in non-metallic trunking			(F) Thermoplastic / SWA cables		(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(I) other - state:		N/A			
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa			Max. disconnection time (BS 7671) (s)	Protective device			RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max. measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons					
					Live (mm ²)	cpc (mm ²)			BS (EN)	Type	Rating (A)			Short-circuit capacity (kA)	Ring final circuits only (measured end to end)	(Line) r ₁	(Neutral) r _n	(cpc) r ₂	(R ₁ + R ₂)	All circuits (complete at least one column)				Live / Live (MΩ)	Live / Earth (MΩ)	Test voltage DC (V)	RCD (✓)	AFDD (✓)	
13L1	Spare																												
13L2	Lights: Training Rm	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.26		✓	0.58		N/A	N/A						
13L3	Lights: Male Locker	B	B	9	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.25		✓	0.63		N/A	N/A						
14L1	Spare																												
14L2	Lights: Armoury	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.26		✓	0.57		N/A	N/A						
14L3	Spare																												
15L1	Spare																												
15L2	Lights: WC's	B	B	2	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.22		✓	0.54		N/A	N/A						
15L3	Spare																												
16L1	Battery Supply	B	B	1	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				LIM		LIM		LIM		N/A	N/A					
16L2	Spare																												
16L3	Spare																												
17L1	Spare																												
17L2	Lights: Training Rm	B	B	3	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.32		✓	0.64		N/A	N/A						
17L3	Spare																												
18L1	Spare																												
18L2	Lights:Plant/Repro	B	B	8	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.19		✓	0.59		N/A	N/A						
18L3	Spare																												

DISTRIBUTION BOARD (DB) DETAILS	DB designation: DB9	Location of DB: Plant Room
TESTED BY		
Name (capital): BRIAN MCCARTHY	Signature:	Position: Electrician
Date: 07/10/2021		Date: 07/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 9-TP)	Nominal voltage: (400) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (100) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (✓)	Operating time (N/A) ms
Characteristics at this DB	Earth electrode resistance: (N/A) Ω	Earth fault loop impedance: (N/A) Ω

CONTINUATION SHEET: ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 - Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing: N/A

CODES for Type of wiring		Thermoplastic insulated / sheathed cables		Thermoplastic cables in metallic conduit		Thermoplastic cables in non-metallic conduit		Thermoplastic cables in metallic trunking		Thermoplastic cables in non-metallic trunking		Thermoplastic / SWA cables		Thermosetting / SWA cables		Mineral-insulated cables		(O) other - state		N/A					
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max disconnection time (BS 7671) (s)	Protective device				RCD current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			RCD operating time	Test buttons			
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating	Short-circuit capacity (kA)			Operating current, I _n (mA)	Ring final circuits only (measured end to end)	All circuits (complete at least one column)	Live / Live (MΩ)	Live / Earth (MΩ)	Test voltage DC	Polarity		Max measured earth fault loop impedance, Z _s (Ω)	RCD (✓)	AFDD (✓)	
1L1	Spare																								
1L2	Sockets: D40/41/44	B	B	8	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.52	0.52	0.16	0.23			200	500	✓	17	✓	N/A
1L3	Sockets: D45/46/47	B	B	8	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.63	0.65	0.19	0.33			200	500	✓	17	✓	N/A
2L1	Spare																								
2L2	Sockets: D52/53	B	B	6	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.61	0.63	0.19	0.33			200	500	✓	18	✓	N/A
2L3	Fixed Power: D56/57	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.32			200	500	✓		N/A	N/A
3L1	Sockets: Corridor	B	B	3	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.74	0.72	0.34	0.14			200	500	✓	19	✓	N/A
3L2	Fixed Power: Server	B	B	1	4	2.5	0.4	60898	C	32	6	N/A	0.68				LIM			LIM	N/A				
3L3	Sockets: Locker Rm	B	B	4	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.42	0.47	0.27	0.00			200	500	✓	18	✓	N/A
4L1	Hand Dryer: Male Cadet	B	B	1	4	2.5	0.4	60898	C	20	6	N/A	1.09				0.14			200	500	✓		N/A	N/A
4L2	Fixed Power: D42	B	B	1	4	2.5	0.4	60898	C	32	6	N/A	0.68				0.27			200	500	✓		N/A	N/A
4L3	Spare																								
5L1	Fixed Power: Corridor	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09	0.56	0.55	0.22	0.01			200	500	✓		N/A	N/A
5L2	Sockets: Training Hall	B	B	3	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.51	0.49	0.13	0.05			200	500	✓	18	✓	N/A
5L3	Spare																								
6L1	Sockets: D18/Corridor	B	B	4	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.68	0.6	0.15	0.32			200	500	✓		N/A	N/A
6L2	Sockets: Training Hall	B	B	3	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.71	0.73	0.15	0.33			200	500	✓	18	✓	N/A
6L3	Spare																								

DISTRIBUTION BOARD (DB) DETAILS	DB designation: DB10	TESTED BY	Name (capital): BRIAN MCCARTHY	Position: Electrician
(to be completed in every case)	Location of DB: Plant Room	Signature: 	Date: 08/10/2021	Date: 08/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 10-TP)	Nominal voltage: (400...) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (100) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (✓)	Operating time (N/A...) ms
Characteristics at this DB	Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (✓)
		Z_s (0.21...) Ω
		I_{pf} (1.2...) kA



APPROVED
CONTRACTOR

Electrical and
Plumbing Contractors



This continuation sheet is not valid if the serial number is not the same as the corresponding certificate or report.

24273861

ISN18C

CONTINUATION SHEET: ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS

Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS

Circuits/equipment vulnerable to damage when testing N/A

SCHEDULE 8S 8S20 8S21 8S22																											
CODES for Type of wiring			(A) Thermoplastic insulated / sheathed cables		(B) Thermoplastic cables in metallic conduit		(C) Thermoplastic cables in non-metallic conduit		(D) Thermoplastic cables in metallic trunking		(E) Thermoplastic cables in non-metallic trunking		(F) Thermoplastic / SWA cables		(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(I) other - state:		N/A						
Circuit number	Circuit description	Type of wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max disconnection time (BS 7671) (s)	Protective device				RCD current, I _{pn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Max. measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons				
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating	Short-circuit capacity (kA)			Operating current, I _n (A)	Ring final circuits only (measured end to end)	(Line) r ₁	(Neutral) r _n	(cpc) r ₂	All circuits (complete at least one column)	Live / Live (MΩ)			Live / Earth (MΩ)	Test voltage DC (V)	Polarity	RCD (✓)	AFDD (✓)
13L1	Spare																										
13L2	Fixed Power: WC	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09														
13L3	Sockets: D15/16	B	B	6	2.5	2.5	0.4	60898	C	20	6	N/A	1.09	0.55	0.56	0.18	0.23	200	500	✓					N/A		
14L1	Fixed Power: Reception	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09					200	500	✓					N/A		
14L2	Sockets: Armoury	B	B	3	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.56	0.57	0.23	0.11	200	500	✓		18			✓	N/A	
14L3	Hand Dryer	B	B	1	4	2.5	0.4	60898	C	20	6	N/A	1.09				0.16	200	500	✓						N/A	
15L1	Spare																										
15L2	Spare																										
15L3	Sockets: D59	B	B	4	2.5	2.5	0.4	61009	C	32	6	30	0.68	0.91	0.87	0.36	0.18	200	500	✓		11				✓	N/A
16L1	Spare																										
16L2	Spare																										
16L3	Water Heater	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.16	200	500	✓							N/A
17L1	Spare																										
17L2	Hand Dryer	B	B	1	4	2.5	0.4	60898	C	20	6	N/A	1.09				0.13	200	500	✓							N/A
17L3	Fixed Power: Drying Room	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.17	200	500	✓							N/A
18L1	Spare																										
18L2	Hand Dryer	B	B	1	4	2.5	0.4	60898	C	20	6	N/A	1.09				0.13	200	500	✓							N/A
18L3	Socket: Plant Room	B	B	1	2.5	2.5	0.4	60898	C	20	6	N/A	1.09				0.01	200	500	✓							N/A

DISTRIBUTION BOARD (DB) DETAILS DB designation: DB10
TESTED BY Name (capital): BRIAN MCCARTHY
Signature: Date: 08/10/2021
Electrician Position:
Date: 08/10/2021

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 10-TP) Nominal voltage: (400 V) No. of phases: (3)
Overcurrent protection device for the distribution circuit Type: (BS EN 88-2) Rating: (100) A
Associated RCD (if any) Type: (BS EN N/A) No. of poles: (N/A) I_{Δn} (N/A) mA Operating time (N/A) ms
Characteristics at this DB Confirmation of supply polarity: (✓) Phase sequence confirmed (where appropriate): (✓) Z_s (0.21) Ω I_{pr} (1.2) kA

TEST INSTRUMENTS (enter serial number against each instrument used)

Multi-function: (8189065) Continuity: (N/A)
Insulation resistance: (N/A) Earth fault loop impedance: (N/A)
Earth electrode resistance: (N/A) RCD: (N/A)

This form is based on the model forms shown in Appendix 6 of BS 7671

Published by Certsure LLP Certsure LLP operates the NICEIC & ELECSA brands @ Copyright Certsure LLP (July 2018)

Warwick House, Houghton Hall Park, Houghton Regis, Dunstable, LU5 5ZX

* Where figure is not taken from BS 7671, state source: (N/A)

CONTINUATION SHEET:

ELECTRICAL INSTALLATION CERTIFICATES & ELECTRICAL INSTALLATION CONDITION REPORTS
Issued in accordance with BS 7671: 2018 – Requirements for Electrical Installations

XXX / IPN : SCHEDULE OF CIRCUIT DETAILS AND TEST RESULTS
(Delete as appropriate)

Circuits/equipment vulnerable to damage when testing: 5L1, 5L2, 6L1, 6L2, 7L2, 7L3

CODES for Type of wiring										(A) Thermoplastic insulated / sheathed cables										(B) Thermoplastic cables in metallic conduit		(C) Thermoplastic cables in non-metallic conduit		(D) Thermoplastic cables in metallic trunking		(E) Thermoplastic cables in non-metallic trunking		(F) Thermoplastic / SWA cables		(G) Thermosetting / SWA cables		(H) Mineral-insulated cables		(I) other - state:		N/A			
Circuit number	Circuit description	Type of Wiring (see Codes)	Reference Method (BS 7671)	Number of points served	Circuit conductor csa		Max. disconnection time (BS 7671) (s)	Protective device			RCD Operating current, I _{Δn} (mA)	Maximum permitted Z _s for installed protective device* (Ω)	Circuit impedances (Ω)				Insulation resistance			Polarity	Max measured earth fault loop impedance, Z _s (Ω)	RCD operating time (ms)	Test buttons																
					Live (mm ²)	cpc (mm ²)		BS (EN)	Type	Rating (A)			Short-circuit capacity (kA)	(Line) I ₁	(Neutral) I _n	(cpc) I ₂	(R ₁ + R ₂)	R ₂	Live / Live (MΩ)				Live / Earth (MΩ)	Test voltage DC (V)	RCD (✓)	AFDD (✓)													
1L1	Sockets: RHQ Stores	B	B	3	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.52	0.52	0.21	0.11		200	500	✓	0.2	N/A	N/A															
1L2	Sockets: SQN Stores	B	B	2	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.63	0.66	0.25	0.17		200	500	✓	0.33	N/A	N/A															
1L3	Sockets: Below DB	B	B	2	2.5	2.5	0.4	60898	C	20	6	N/A	1.09	0.08	0.08	0.02	0.00		200	500	✓	0.17	N/A	N/A															
2L1	Sockets: RHQ Stores	B	B	2	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.52	0.52	0.12	0.09		200	500	✓	0.15	N/A	N/A															
2L2	Sockets: SHQ Stores	B	B	3	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.64	0.64	0.19	0.12		200	500	✓	0.28	N/A	N/A															
2L3	Spare																																						
3L1	Sockets: RHQ Stores	B	B	2	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.44	0.42	0.34	0.13		200	500	✓	0.25	N/A	N/A															
3L2	Sockets: Stores Office	B	B	8	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.27	0.26	0.1	0.14		200	500	✓	0.26	N/A	N/A															
3L3	Sockets: SQN Office	B	B	3	2.5	2.5	0.4	60898	C	32	6	N/A	0.68	0.62	0.64	0.26	0.23		200	500	✓	0.39	N/A	N/A															
4TP	Spare																																						
5L1	Lights: RHQ Stores	B	B	10	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.32		200	250	✓	0.83	N/A	N/A															
5L2	Lights: Stores Office	B	B	2	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.19		200	250	✓	0.42	N/A	N/A															
5L3	Spare																																						
6L1	Lights: RHQ Stores	B	B	9	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.35		200	250	✓	0.85	N/A	N/A															
6L2	Lights: SQN Stores	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.25		200	250	✓	0.76	N/A	N/A															
6L3	Spare																																						
7L1	Spare																																						
7L2	Lights: SQN Stores	B	B	6	2.5	2.5	0.4	60898	C	10	6	N/A	2.19				0.3		200	250	✓	0.83	N/A	N/A															

DISTRIBUTION BOARD (DB) DETAILS (to be completed in every case)	DB designation: DB11	Location of DB: RHQ Stores	TESTED BY Name (capitalist): BRIAN MCCARTHY Signature:	Position: Electrician Date: 27/10/2021
---	----------------------	----------------------------	---	---

TO BE COMPLETED ONLY IF THE DB IS NOT CONNECTED DIRECTLY TO THE ORIGIN OF THE INSTALLATION

Supply to DB is from: (MSB1 - 11-TP)	Nominal voltage: (400) V	No. of phases: (3)
Overcurrent protection device for the distribution circuit	Type: (BS EN 88-2)	Rating: (100) A
Associated RCD (if any)	Type: (BS EN N/A)	No. of poles: (N/A)
Confirmation of supply polarity: (✓)	Phase sequence confirmed (where appropriate): (✓) Z _s 0.29	Operating time (N/A) ms
Characteristics at this DB	Insulation resistance: (N/A)	Earth fault loop impedance: (N/A)
	Earth electrode resistance: (N/A)	RCD (N/A)

TEST INSTRUMENTS (enter serial number against each instrument used)	
Multi-function: (8189065)	Continuity: (N/A)
Insulation resistance: (N/A)	Earth fault loop impedance: (N/A)
Earth electrode resistance: (N/A)	RCD: (N/A)



This continuation sheet is not valid if the serial number has been defaced or altered

24273861

N18C

GENERAL CONTINUATION SHEET

NOTES

General Condition Of the Installation

There has been some ingress of water to the light fittings in the cadet WC due to leaking pipework above. Whilst these are still working and with reasonably good insulation readings, these will corrode and fail over the coming months. Replacement recommended.

Original (to the person ordering the work)



This continuation sheet is not valid if the serial number has been defaced or altered

24273861

N18C

GENERAL CONTINUATION SHEET

NOTES

Operational Limitations

The offices are in continual use which didn't allow disconnection/isolation of some circuits to carryout dead tests. The lighting circuits contain sensitive electronic parts which limited the insulation resistance tests to L/E & N/E @ 250V only.

Original
(to the person ordering the work)

NOTES FOR RECIPIENT

THIS CONDITION REPORT IS AN IMPORTANT AND VALUABLE DOCUMENT WHICH SHOULD BE RETAINED FOR FUTURE USE

The purpose of periodic inspection is to determine, so far as is reasonably practicable, whether an electrical installation is in a satisfactory condition for continued service. This report provides an assessment of the condition of the electrical installation identified overleaf at the time it was inspected and tested, taking into account the stated extent of the installation and the limitations of the inspection and testing.

This report has been issued in accordance with the national standard for the safety of electrical installations, *BS 7671:2018 – Requirements for Electrical Installations*.

The report identifies any damage, deterioration, defects and/or conditions found by the inspector which may give rise to danger (see PART 6), together with any items for which improvement is recommended. If you were the person ordering this report, but not the user of the installation, you should pass this report, or a full copy of it including these notes, the schedules and additional pages (if any), immediately to the user.

This report should be retained in a safe place and shown to any person inspecting or undertaking further work on the electrical installation in the future. If you later vacate the property, this report will provide the new user with an assessment of the condition of the electrical installation at the time the periodic inspection was carried out.

Where the installation incorporates a residual current device (RCD) there should be a notice at or near the device stating that it should be tested every six months. For safety reasons it is important that this instruction is followed.

For safety reasons, the electrical installation should be re-inspected at appropriate intervals by a skilled person or persons, competent in such work. NICEIC* recommends that you engage the services of an NICEIC Approved Contractor for the inspection.

The recommended date by which the next inspection should be carried out is stated in PART 5 of this report. There should also be a notice at or near the main switchboard or distribution board/consumer unit indicating when the next inspection of the installation is due.

Only an NICEIC Approved Contractor or Conforming Body is authorised to issue this NICEIC Electrical Installation Condition Report. You should have received the report marked 'Original' and the Approved Contractor should have retained the report marked 'Duplicate'.

This report form is intended to be issued only for the purpose of reporting on the condition of an existing electrical installation and must not be issued to certify new electrical installation work including the replacement of a distribution board or consumer unit.

The report consists of at least six numbered pages. Additional numbered pages may have been provided to permit further relevant information relating to the installation to be recorded. For installations having more than one distribution board or more circuits than can be recorded on PART 12, one or more additional *Schedules of Circuit Details and Test Results* should form part of the report. The report is invalid if any of the schedules identified in PART 10 are missing. The report has a printed serial number, which is traceable to the Contractor to which it was supplied.

PART 7 (Details and limitations) should identify fully the extent of the installation covered by this report and any limitations on the inspection and testing. The inspector should have agreed these aspects with the person ordering the report and with other interested parties (licensing authority, insurance company, mortgage provider and the like) before the inspection was carried out.

Operational limitations may have been encountered during the inspection such as inability to gain access to parts of the installation or to an item of equipment. The inspector should have noted any such limitations in PART 7. It should be noted that the greater the limitations applying to a report, the less its value from the safety aspect.

A declaration should have been given by the inspector in PART 4 of the report. The declaration must reflect the statement given in PART 3, which summarises the observations and recommendations made in PART 6. Where one or more observations have been made in PART 6, the Classification code given to each by the inspector indicates the degree of urgency with which remedial action needs to be taken to restore the installation to a safe working condition.

Where the inspector has indicated an observation as code C1 (danger present) **the safety of those using the installation is at risk**. Wherever practicable, items classified as (C1) should be made safe on discovery, and it is recommended that a skilled person(s) competent in electrical installation work undertakes the necessary remedial work immediately.

Where the inspector has indicated an observation as code C2 (potentially dangerous) **the safety of those using the installation may be at risk**, and it is recommended that a skilled person(s) competent in electrical installation work undertakes the necessary remedial work as a matter of urgency.

Where the inspector has indicated that an item requires further investigation (FI), the investigation should be carried out without delay to determine whether danger or potential danger exists. For further guidance on the Classification codes, please see the reverse of page 2.

Where the installation can be supplied by more than one source, such as the public supply and a standby generator or microgenerator, this should be identified in PART 8 *Supply Characteristics and Earthing Arrangements*, and the *Schedules of Circuit Details and Test Results* (PART 12) compiled accordingly.

Where inadequacies in the intake equipment have been observed (Item 1 of PART 10), the person ordering the inspection should inform the distributor and/or supplier as appropriate.

Should the person ordering this report have reason to believe that it does not reasonably reflect the condition of the electrical installation reported on, that person should in the first instance raise the specific concerns in writing with the Approved Contractor. If the concerns remain unresolved, the person ordering this report may make a formal complaint to NICEIC, for which purpose a complaint form is available on request.

The complaints procedure offered by NICEIC is subject to certain terms and conditions, full details of which are available upon application. NICEIC does not investigate complaints relating to the operational performance of electrical installations (such as lighting levels), or to contractual or commercial issues (such as time or cost).

** NICEIC is operated by Certsure LLP, a partnership between the Electrical Contractors' Association and the charity, Electrical Safety First. NICEIC maintains and publishes registers of electrical contractors that it has assessed against particular scheme requirements (including the technical standard of electrical work).*

For further information about electrical safety and how NICEIC can help you, visit www.niceic.com

GUIDANCE FOR RECIPIENTS ON THE CLASSIFICATION CODES

Only one Classification code should be given for each recorded Observation

Classification code C1 (Danger present)

Where an observation has been given a Classification code C1, the safety of those using the installation is at risk and immediate remedial action is required.

The person responsible for the maintenance of the installation is advised to take action without delay to remedy the observed deficiency in the installation, or to take other appropriate action (such as switching off and isolating the affected part(s) of the installation) to remove the danger. The NICEIC Approved Contractor issuing this report will be able to provide further advice.

NICEIC makes available 'Electrical Danger Notification' forms to enable inspectors to record, and then to communicate to the person ordering the report, any dangerous condition discovered.

Classification code C2 (Potentially dangerous)

Classification code C2 indicates that, whilst those using the installation may not be at immediate risk, urgent remedial action is required to remove potential danger. The NICEIC Approved Contractor issuing this report will be able to provide further advice.

It is important to note that the recommendation given at PART 5 of this report (Next Inspection) for the maximum interval until the next inspection is conditional upon all items which have been given a Classification code C1 and code C2 being remedied immediately and as a matter of urgency, respectively. It would not be reasonable for the inspector to indicate that the installation is in a satisfactory condition if any observation in this report has been given a code C1 or code C2 classification.

Classification code C3 (Improvement recommended)

Where an observation has been given a Classification code C3, the inspection and/or testing has revealed a non-compliance with the current safety standard which, whilst not presenting immediate or potential danger, would result in a significant safety improvement if remedied. Careful consideration should be given to the safety benefits of improving these aspects of the installation. The NICEIC Approved Contractor issuing this report will be able to provide further advice.

Code FI (Further investigation required without delay)

It should usually be possible for the inspector to attribute a Classification code to each observation without indicating a need for further investigation.

However, where 'FI' has been entered against an observation the inspector considers that further investigation of that observation is likely to reveal danger or potential danger that, due to the agreed extent or limitations of the inspection and/or testing, could not be fully identified at the time.

It would not be appropriate for the inspector to indicate that the installation is in a satisfactory condition if there is reasonable doubt as to whether danger or potential danger exists. Consequently, where the inspector has indicated 'Further investigation required without delay' (FI) the overall assessment of the installation (PART 3) should be marked as 'Unsatisfactory'.

If the inspector has indicated that an observation requires further investigation without delay, the person ordering this report is advised to arrange for the NICEIC Approved Contractor issuing the report (or another skilled person or persons competent in such work) to undertake further examination of that aspect of the installation as a matter of urgency, to determine whether or not danger or potential danger exists.

Further information

Further information on the application of Classification codes, primarily aimed at inspectors but of possible interest to persons ordering condition reports, can be found in Electrical Safety First's Best Practice Guide No 4 *Electrical installation condition reporting: Classification Codes for domestic and similar electrical installations*. The guide can be viewed or downloaded free of charge from www.electricalsafetyfirst.org.uk

For further information about electrical safety and how NICEIC can help you, visit www.niceic.com